



**Titanium Series 4.0 MR16 7W
7MR16G4DIM**



Magnetic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																									
				HALO CAN				ELCO CAN					NORA CAN			ELCO LTG		ELG transf.						ESBCO transf.					
				1	2	3	4	1	2	3	4	5	1	2	3	1	2	1	2	3	4	5	6	1	2	3	4	5	6
LUTRON	Abella	ABLV-1000M	1000	OK				12%-100%					X			OK		OK						X					
	Maestro	MALV-1000	1000	OK				15%-100%					X			X		X						OK					
	Nova	NTELV-600	600	OK				OK					X			OK		OK						OK					
	Skylark	S-600	600	25%-100%				X					X			20%-100%		X						OK					
	Skylark	SLV-600P	600	15%-100%				20%-100%					X			20%-100%		15%-100%						OK					
LEVITON	Sure Slide	6613-P	600	15%-100%				20%-100%					X			OK		15%-100%						OK					
	VIZA+	VPM10	1000	OK				15%-100%					X			OK		OK						X					
COOPER	Aspire	9539	600	OK				OK					X			OK		OK						OK					

Table Key
 OK= Fully compatible
 __ - __% = Compatible within this range

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



**Titanium Series 4.0 MR16 7W
7MR16G4DIM**



Electronic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																													
				Hatch												Ligtech																	
				RS 12-80M						RS 12-60M(LED)						RS 12-60M						LRT75						LRT60					
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6
LUTRON	Skylark	SELV-300P	600	OK																													
LEVITON	Sure Slide	6613-P0W	1000	OK						X	OK						X	OK						OK									
		6615-P0W	1000	X	OK						X						X	OK															

Table Key
 OK= Fully compatible
 __-__% = Compatible within this range

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.