



Titanium Series 4.0 T8 17W,15W & 10W DIR
 For models: 17T8G4/4F/xxx/DIR, 15T8G4/4F/xxx/DIR, 10T8G4/2F/xxx/DIR
 Where xxx means 824-965 which indicates CRI and color temperature

Instant Start Ballast Compatibility

Brand	Model	Compatibility
Philips - Advance	ICN-1P32-N	OK
Philips - Advance	ICN-2P32-N	OK
Philips - Advance	ICN-3P32-N	OK
Philips - Advance	IOPA-2P32-N	OK
Philips - Advance	IOPA-3P32-N	OK
Philips - Advance	IOPA-1P32-HL-N	OK
Philips - Advance	IOPA-2P32-LW-N	OK
Philips - Advance	IOPA-4P32-LW-N	OK
Philips - Advance	IOP-2P32-HL-N	OK
Philips - Advance	IOP-3P32-N	OK
Philips - Advance	IOP-4P32-LW-N	OK
Philips - Advance	IOPA-4P32-SC	ONLY 277V
Philips - Advance	ICN-132-MC	X
GE - Ultramax	GE132-MV-N	OK
GE - Ultramax	GE232-MV-N	OK
GE - Ultramax	GE332-MV-N	OK
GE - Ultramax	GE132MAX-L	OK
GE - Ultramax	GE232MAX-L	OK
GE - Ultramax	GE332MAX-L	OK
GE - Ultramax	GE132MAX-N	OK
GE - Ultramax	GE232MAX-N	OK
GE - Ultramax	GE232MAX-H	OK
GE - Ultramax	GE332MAX-H	OK
Howard	EP2/32IS/MV/MC/HE	OK
Howard	EP3/32IS/MV/MC/HE	OK
Howard	EPL3/32IS/MV/SC/HE	OK
Howard	EP4/32IS/MV/MC/HE	OK
Sylvania	QHE 2X40DL/UNV ISN-SC	OK
Sylvania	QHE 2X32T8/UNV ISN-SC	OK
Sylvania	QTP 3X32T8/UNV ISN-SC	OK
Plusrite	BAF232IS/MV	OK
Plusrite	BAF332IS/MV	OK
Plusrite	BAF432IS/MV	OK
Triad	B232IUNVHP-N	OK
Triad	B332IUNVHP-A	OK
Triad	B432IUNVHP-A	OK
EIKO	PM-2X32T8-UNV-IS-L	OK
Green Hill	GH2P59ISUNV	OK
SOLA	E-758-U-259-SC	OK
Eiko	PM-4X32T8-UNV-IS-H	ONLY 277V
Concord	BL-3040LB-2	X

*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.