



**Titanium Series 4.0 MR16 7.5W NF25 & FL36
7.5MR16G4DIM**



Magnetic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																									
				HALO CAN				ELCO CAN					NORA CAN			ELCO LTG		ELG transf.						SEBCO transf.					
				1	2	3	4	1	2	3	4	5	1	2	3	1	2	1	2	3	4	5	6	1	2	3	4	5	6
LUTRON	Abella	ABLV-1000M	1000	X			OK	OK					X			X		OK						X					
	Maestro	MALV-1000	1000	X				OK					X			X		OK						X					
	Nova	NTELV-600	600	OK				OK					X			OK		OK						OK					
Skylark	Skylark	S-600	600	20%-100%				X					X			X		X						OK					
	Skylark	SLV-600P	600	20%-100%				X					X			20%-100%		X						X					
LEVITON	Sure Slide	6613-P	600	15%-100%				20%-100%					X			15%-100%		25%-100%						OK					
	VIZA+	VPM10	1000	X				OK					X			OK		X						OK					
COOPER	Aspire	9539	600	OK				OK					X			OK		X						OK					

Table Key
 OK= Fully compatible
 __ - __% = Compatible within this range
 X= Incompatible

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



**Titanium Series 4.0 MR16 7.5W NF25 & FL36
7.5MR16G4DIM**



Electronic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																													
				Hatch												Lightech																	
				RS 12-80M						RS 12-60M(LED)						RS 12-60M						LRT75						LRT60					
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6
LUTRON	Skylark	SELV-300P	600	OK																													
LEVITON	Sure Slide	6613-POW	1000	OK						X	OK						OK																
		6615-POW	1000	OK						X						OK																	

Table Key
OK= Fully compatible
 __ - __% = Compatible within this range
X= Incompatible

***GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.**