



**Titanium Series T8 10W DIR**  
 For models: 10T8/3F/xxx/DIR  
 Where xxx means 824-965 which indicates CRI and color temperature

**Electronic Ballast Compatibility**

Series	Model	Type	Compatibility
Philips - Advance	ICN-1P32-N	IS	OK
Philips - Advance	ICN-2P32-N	IS	OK
Philips - Advance	ICN-3P32-N	IS	OK
Philips - Advance	ICN-4P32-N	IS	OK
Philips - Advance	IOPA-1P32-LW-N	IS	OK
Philips - Advance	IOPA-2P32-LW-N	IS	OK
Philips - Advance	IOP-2P32-LW-N	IS	OK
Philips - Advance	IOP-4P32-LW-N	IS	OK
Philips - Advance	IOP-3P32-N	IS	OK
Philips - Advance	ICN-132-MC	IS	OK
Philips - Advance	REZ-2S32-SC	PS	OK
Philips - Advance	VEZ-132-SC	PS	OK
Philips - Advance	VEZ-2S32-SC	PS	OK
Philips - Advance	IZT-132-SC	PS	OK
Philips - Advance	IZT-2PSP32-SC	PS	OK
Philips - Advance	ILV-2S32-SC	PS	OK
Philips - Advance	IOPA-4P32-SC	IS	277V ONLY
Philips - Advance	ICN-4P32-SC	IS	277V ONLY
Philips - Advance	IOP-2P32HL-SC	IS	X
GE - Ultramax	GE232MAX-L/ULTRA	IS	OK
GE - Ultramax	GE232MAX-N/ULTRA	IS	OK
GE - Ultramax	GE232MAX-H/ULTRA	IS	OK
GE - Ultramax	GE232MAXP-N/ULTRA	IS	OK
GE - Ultramax	GE232MAXP-H/ULTRA	IS	OK
GE - Ultramax	GE332MAX-N/ULTRA	IS	OK
GE - Ultramax	GE332MAX-H/ULTRA	IS	OK
GE - Ultramax	GE432MAX-L/ULTRA	IS	OK
GE - Ultramax	GE432MAX-N/ULTRA	IS	OK
GE - Proline	GE-232MV-N	IS	OK
GE - Proline	GE-332MV-N	IS	OK
GE - Proline	GE-432-120-N	IS	OK
GE - Ultrastart	GE-232-120-PS-N	PS	OK
Universal - Triad	B132IUNVHP-N	IS	OK
Universal - Triad	B232IUNVHP-N	IS	OK
Universal - Triad	B332IUNVHP-N	IS	OK
Universal - Ballastar	B232PUS50-A	PS	OK
Plusrite	BAF232IS/MV	IS	OK
Plusrite	BAF432IS/MV	IS	OK
Howard	EP2/32IS/MV/MC/HE	IS	OK
Howard	EPL3/32IS/MV/SC/HE	IS	OK
Sylvania	QTP 4x32T8/UNV ISN-SC	IS	OK
Sylvania	QHE 2x32T8/UNV ISN-SC	IS	OK
Fulham	WHSG4-UNV-T8-IS	IS	OK
Utilitech	YZ-232	IS	OK
EIKO - Powermaster	PM-2x32T8-UNV-IS-L	IS	OK
Espen	VE232MVHIPHE	IS	OK
Sola	E-758-F-232-SC	IS	X

\*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.