

DDS15-BDZ



UPC Code: 07847772852

Country of Origin: China

Electronic Timer Switches

Brand Features

The next generation of lighting control technology is here with the new Decora® Digital Controls with Bluetooth® technology - a powerful device combining the best of Leviton timer functions with today's technology. Just use your smartphone or tablet and the Decora Digital Dimmer & Timer app to control, adjust and time lighting for daily activities or to ensure a "lived-in" look while away. Decora Digital Controls with Bluetooth technology provide local control within a 30 foot* range without the need of a hub, gateway or internet connection.

*30-foot Bluetooth range: Range may vary depending on specific conditions on installation, configuration of walls, obstacles and other factors.

Item Description

Decora Digital Switch and 24 hour Timer 1800W Incandescent (120V), 15A Fluorescent (120V), 6A Fluorescent (277V), 5A 600W LED/CFL (120V), 15A Resistive (120V), 1/2 HP Motor (120V), Single Pole and 3-way/multi-location control with LED locator. White face assembled on device, Ivory and Light Almond faces included. Neutral wire required

Technical Information

Product Features

Switch Type: Single-Pole, 3-Way or More Applications

Style Name: Decora

Timer Type: 24 Hour

Type: Digital

Wireless Connectivity: Bluetooth

Load Type: Incandescent, LED, CFL, Fluorescent, Resistive, Motor

Load Rating: 1800W Incandescent, 15A Fluor (120V), 6A Fluor (277V), 600W LED/CFL, 15A Resistive, 1/2 HP Motor

Voltage: 120/277VAC, 60Hz

LED Color: Green

Light: LED Indicator

Action: Rocker Switch for ON/OFF

Wallplate: Order Separately

Color: White, Ivory, Light Almond

Standards and Certifications: CSA, NOM, Bluetooth SIG, FCC, Title 24 Compliant

Warranty: 5 Year Limited

Ordering Notes: Incl White, Ivory and Light Almond Color Kit

Available Colors: Ivory-I Wht-W Gry-G Blk -E Brwn-B Light Almond-T

Wiring Notes: Neutral required

Features and Benefits

- Digital circuitry provides programmable on/off lighting schedules
- Ability to set maximum light level for energy savings
- App is Compatible with Apple and Android smartphones or tablets
- Uses simple, intuitive on-screen menu options
- Individually control and program switches within the home

- Each device can be uniquely named for easy identification
- Flexibility to program timed events weekdays, weekends or any combination of days at set or random times
- Astronomical clock automatically adjusts to local sunrise/sunset times
- Automatic daylight saving time adjustment
- Countdown sleep timer can be set for up to 12 hours
- LED locator light can be turned off via app
- Single pole or 3-way/multi-location control with Decora Digital remote (sold separately)
- No fins for multi-gang installation
- Built-in radio/TV interference filter
- Neutral wire required

