



## PL EDGE Series PL H 9.5W DIR

For models: 9.5PLH/xxx/DIR Where xxx means 818-965 which indicates CRI and color temperature

**Electronic Ballast Compatibility** 

Brand	Model	Compatibility
Philips - Advance	ICF-2S13-M1-BS-QS	OK
Philips - Advance	ICF-2S18-M1-BS-QS	OK
Philips - Advance	ICF-2S26-M1-BS-QS	OK
Philips - Advance	ICF-2S18-H1-LD	OK*
Philips - Advance	ICF-2S26-H1-LD	OK
Philips - Advance	ICF-2S26-H1-LD-QS	OK
Philips - Advance	ICF-2S42-M2-LD	OK
Philips - Advance	IZT-2S26-M5-BS	OK
Philips - Advance	IZT-2S42-M5-BS	OK
Philips - Advance	VEZ-1T42-M2-BS	OK
Sylvania	QTP 1/2x13CF/UNV DM	OK
Sylvania	QTP 2x26CF/UNV DM	OK
Sylvania	QTP 2x26/32/42CF/UNV DM	OK**
Hatch	HC213PS/UV/D	OK
Hatch	HC226PS/UV/D	OK
Hatch	HC242PS/UV/D	OK
Triad/Universal Lighting	C213UNVBES	OK
Triad/Universal Lighting	C213UNVME	OK
Triad/Universal Lighting	C218UNVME	OK
Triad/Universal Lighting	C2642UNVME	OK
Howard Lighting	EP2/13CF/MV/2	OK
Howard Lighting	EP2/18CF/MV/2	OK
Howard Lighting	EP2/26CF/MV/2	OK
Howard Lighting	EP2/42CF/MV/2	OK
Sola	E-724-U-226-M1-S	OK
Fulham	WH2-277-L	OK
Fulham	WH3-277-L	OK
Fulham	WH4-277-L	OK
Fulham	RHA-UNV-213-C	OK**
Fulham	RHA-UNV-226-C	OK**
Fulham	RHA-UNV-242-C	OK OK
Fullialli		OI.
WARNING  DO NOT INSTALL LAMPS WITH THE FOLLOWING BALLASTS. DO NOT INSTALL LAMPS WITH BALLASTS NOT ON  THIS LIST UNTIL COMPATIBILITY IS CONFIRMED WITH OUR TECHNICAL TEAM.  Some older ballast versions can cause over heating and damage to lamp and fixture. In case of doubt about compatibility, please contact us: techsupport@greencreative.com		
Philips - Advance	REB-2S26M-BS	X
Philips - Advance	H-2B13-TP-BLS	X
Sylvania	QTP 2x26CF/UNV QS	X
Sylvania	QTP 2x26CF/UNV BS	X
Sylvania	QTP 2x26CF/UNV TS	X
Sylvania	QTP 2x26/32/42CF/UNV BM	X
Sylvania	QTP 2x26/32/42CF/UNV TM	X
Sylvania	QTP 1/2x18CF/UNV TS	X
Sylvania	QTP 1/2xCF/UNV BM	X
Sylvania	QTP 1/2xCF/UNV TM	X
Sylvania	M1/2-CF-B-M-UNIV	X
Sylvania	M2-CF-18-Q-S-277V	X
Sylvania	QT2x32/277V IS-SC	X
Universal - Triad	CBT213L-120S	X
Antron	CSD-132PBM	X
Fulham	LH1-277-L	X
Keystone	KTEB-226-UV-TP-PIC-DW	X
AC Electronics	CSD-332PBM	X
AC Electronics	EST-V VUDS	Y

AC Electronics Standard Topaz Watran

> Robertson Hatch

Energy Savings

\*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed electronic ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

EST-A40PS 31003STD E1321-UV-S B2642UNV/ME-TPZ DBC218MVRSN M1-CF-42-B-S-120

RED2L10-277

FR1800 ES-1-CFH-42/32/26-UNV-C

<sup>\*</sup> Not compatible with older versions of this ballast

<sup>\*\*</sup> Compatible in 2-lamp installations only