



Titanium Series MR16 8.5W 8.5MR16DIM



Magnetic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)															
				HALO CAN			ELCO			Juno	NORA			ESBCO			ELG		
				1	2	3	1	2	3	1	1	2	3	1	2	3	1	2	3
LUTRON	Abella	ABLV-1000M	1000	OK**			15-100%*			X	X			X			X		
	Maestro	MALV-600	600	OK			15-100%			OK	X			X			X		
	Skylark	SLV-600P	600	OK			OK			X	15-100%			OK			X		
Legrand	Harmony	H703PTU	600	OK			15-100%			15-100%	15-100%			OK			OK		
	Adorne	ADTP703TU	700	OK			OK			X	15-100%			OK			OK		
LEVITON	Sure Slide	6613-PL	600	OK			X			X	OK			OK			X		
	VIZA+	VPM10-1LX	1000	OK			OK			X	X			X			OK		
COOPER	Devine	DAL06P	300	OK			X			X	X			X			X		
	Aspire	9536	600	X			X			X	X			X			X		

*Minimum 2 lamps

**Minimum 3 lamps

Table Key

OK= Fully compatible

__ - __% = Compatible within this range

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



**Titanium Series MR16 8.5W
8.5MR16DIM**



Electronic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																											
				Hatch																											
				RS12-60M-LED (DC1340)						RS12-60M (DC1124LED)						RS12-60M (DC1130)						RS12-80M (DC1412)						RS12-30M (DC1413)			RS12-15M- LED
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	1
LUTRON	Rotary	6B38	600	X																											
	Nova	NTELV-300	300	10-75%						X						X						5-75%						X			X
LEVITON	Decora	6615P	1000	X						X						OK						X						X			X

Table Key

OK= Fully compatible

__-__% = Compatible within this range

X= Incompatible

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.