



GLEAR 25W EQUIVALENT FLAME-TIP LED CANDLE

Advanced Driver-Free LEDs that look and feel like traditional incandescent

PRODUCT FEATURES

- True LED Replacement for Incandescent Lamps
- Incandescent Appearance & Uniform Light Quality
- Clear Glass Lamp with Optical Diffuser
- Integrated Driver-Free System
- Smooth Dimming System
- Lighting Design Lab Listed
- Extended 5-Year Warranty


ENERGY SAVINGS—OVER THE LIFE OF THE LAMP¹

DESCRIPTION	25W REPLACEMENT ¹		
Annual Electric Bill Savings	\$11.51		
Total Savings Over LED Lamp Life	\$269.40		
Return on Investment	0.5 Years		











APPLICATIONS











COMMERCIAL LED Series

DIMENSIONS AND WEIGHT

DIMMER	COMPATIBILITY ²

BASE TYPE	LENGTH (inches)	DIAMETER (inches)	WEIGHT (g)				
E12	4.25"	1.25"	52g				
E26	3.95"	1.25"	57g				

BRAND	MODEL NUMBER	DIM RANG	E—1 LAMP	DIM RANGE—3 LAMPS		
		MIN	MAX	MIN	MAX	
LUTRON	DVELV-300P	0%	100%	0%	100%	
	SELV-300P	0%	100%	0%	100%	
	LGCL-153P	20%	100%	20%	100%	
	TGCL-153P	15%	100%	15%	100%	
	SCL-153P	15%	100%	15%	100%	

ORDERING INFORMATION

ONDERING III							
MODEL NUMBER	LAMP TYPE	BASE	WATTS / REPLACES	LUMENS	сст	APPLICATIONS	WARRANTY
LCA12C18024K1	Clear—Flame Tip	E12	3.1W / 25W	180lm	2400k	DAMP	50,000 hours
LCA12C18027K1	Clear—Flame Tip	E12	3.1W / 25W	180lm	2700K	DAMP	50,000 hours
LCA12C20024K1	Clear—Flame Tip	E12	4.0W / 25W	200lm	2400K	DIMMABLE DAMP	50,000 hours
LCA12C20027K4	Clear—Flame Tip	(E12)	(4.0W / 25W)	200lm	(2700K)	DAMP	(50,000 hours)
LCA12C24024K1	Clear—Flame Tip	E12	4.5W / 25W	240lm	2400K	DIMMABLE DAMP	50,000 hours
LCA12C24027K3	Clear—Flame Tip	E12	4.5W / 25W	240lm	2700K	DIMMABLE	50,000 hours
LCA26C24024K1	Clear—Flame Tip	E26	4.5W / 25W	240lm	2400K	DIMMABLE	50,000 hours
LCA26C24027K3	Clear—Flame Tip	E26	4.5W / 25W	240lm	2700K	DIMMABLE	50,000 hours

NOTE 1: Annual savings calculation based on \$0.12/KWH, operating 12-hr/day, \$1 incandescent w/ 1,000-hr life, and LED w/ 50,000-hr life NOTE 2: Dimmer compatibility lists dimmers that has been tested to operate properly under normal conditions. May not include all compatible dimmers.





