Inri **Euri Lighting** 

## INSTALLATION GUIDE MODEL #:

## ET8-2140T-12 / ET8-2150T-12 / ET8-2140T-15 / ET8-2150T-15

This LED lamp is intended to replace fluorescent t8 tube lamps with an ANSI designation 32W/48T8/RS, 32W/48T8

1



## PLEASE REVIEW THE INSTRUCTIONS AND WARNINGS LISTED BELOW PRIOR TO PROPER INSTALLATION

WARNINGS	CAUTIONS
<ul> <li>Risk of fire</li> <li>LED tube bypass ballast installation requires knowledge of luminaire electrical systems.</li> <li>(If you are not a qualified electrician, please do not attempt installation.)</li> <li>Risk of electric shock – turn-off power at source before installation</li> <li>Do not make or alter any open holes in an enclosure of wiring or electrical components during installation.</li> <li>If lamp or luminaire exhibits abnormal operation (buzzing, flickering, minimal light, etc.), turn off power, remove lamp and contact us.</li> </ul>	<ul> <li>Do not use with dimmers.</li> <li>Do not look directly at the operating Bypass Ballast LED T8 Lamp.</li> <li>Do not touch this product with wet hands.</li> <li>Do not disassemble, repair or alter lamp.</li> <li>Designed for indoor applications only.</li> <li>Suitable for damp locations.</li> <li>The luminaires shall be grounded.</li> <li>Avoid contact with lamp pins during installation.</li> <li>This Device is not intended for use with emergency exits or emergency lights.</li> </ul>
	ALIFIED ELECTRICIAN DO YOUR ELECTRICAL WORK.
BYPASS BALLAST INSTALLATION INSTRUCTIONS	
Single Ended Bypassing of Magnetic / Electronic Ballast	
1. Turn-off power before installation.	
2. Remove the existing ballast and existing starter (If present)	
3. Replace fluorescent tube with LED Tube	
4. Remove any pre-existing labels and replace them with the labels provided with this product.	
MAGNETIC BALLAST	ELECTRONIC BALLAST
Traditional Starter	Electronic Ballast b
STEP 1 STEP 2 (continue to step 3 below)	STEP 1 STEP 2 (continue to step 3 below)
STEP 3 FOR BYPASS INSTALLATION SINGLE ENDED INSTALLATION ONLY. (PROFESSIONAL INSTALLATION IS REQUIRED.) LED Tube WARNING! DOUBLE ENDED INSTALLATION IS NOT RECOMMENDED DUE TO POTENTIAL RISK OF FIRE OR ELECTRIC SHOCK	STEP 4