



**Titanium Series MR16 6W
6MR16DIM**



Magnetic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)										
				HALO CAN		ELCO		Juno	NORA		ESBCO		ELG	
				1	2	1	2	1	1	2	1	2	1	2
LUTRON	Abella	ABLV-1000M	1000	X		15-100%*		X		X				OK**
	Maestro	MALV-600	600	X		X		X		OK**		X		X
	Skylark	SLV-600P	600	X		OK		OK		15-100%**		X		15-100%**
Legrand	Harmony	H703PTU	600	X		15-100%		15-100%		OK**		X		OK**
	Adorne	ADTP703TU	700	X		OK		OK		OK		X		OK**
LEVITON	Sure Slide	6613-PL	600	X		OK		OK		OK		X		X
	VIZA+	VPM10-1LX	1000	X		OK		X		OK**		X		OK**
COOPER	Devine	DAL06P	300	X		X		OK		15-100%**		X		OK**
	Aspire	9536	600	X		X		X		X		X		X

*Minimum 2 lamps

**Minimum 3 lamps

<p>Table Key OK= Fully compatible __-__% = Compatible within this range X= Incompatible</p>
--

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a



**Titanium Series MR16 6W
6MR16DIM**



Electronic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																														
				Hatch																														
				RS12-60M-LED (DC1340)						RS12-60M (DC1124LED)						RS12-60M (DC1130)						RS12-80M (DC1412)						RS12-30M (DC1413)					RS12-15M-LED (DC1513K)	
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	1	2
LUTRON	Rotary	6B38	600	X																														
	Nova	NTELV-300	300	OK						OK*						OK						X						OK					OK	
LEVITON	Decora	6615P	1000	X						X						40-100% *						40-100% **						X					X	

*Maximum 2 lamps

**Minimum 2 lamps

Table Key

OK= Fully compatible

__-__% = Compatible within this range

X= Incompatible

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

Electronic			
NO	Model		Lamp
			6MR16DIM/827
1	HATCH	RS12-15M-LED	OK
2		RS12-30M-LED	OK
3		RS12-60M-LED	OK
4		RS12-60M	OK
5		RS12-80M	Flicker
6		RS12-80MGN	Flicker
7		RS24-80M	Flicker
8		RS12-80BFS	OK
9		RS12-60BF-LED	OK
10		RL12-60A	Flicker
11		RS12-80-277M	Flicker
12		RS12-80BF-277	Flicker
13		RL12-75A-277	Flicker
14	LIGHTECH	LET60	OK
15		LET75	OK
16		LET151R	OK

Magnetic			
NO	Model		Lamp
			6MR16DIM/827
1	ELCO	SSH-6626002	OK
2	COOPER	CH50	OK
3	JUNO LIGHTING	VF180-210	OK
4	NORA	TJ-H-277-80-1	OK
5	JUNO LIGHTING	DL1250B-H	OK

Track			
NO	Model		Lamp
			6MR16DIM/827
1	JUNO	T809WH	OK
2	NORA	NORA LIGHTING	OK
3	CONTECH	CTL216T-R	Flicker