



### Titanium Series T5 HE 15W, 12W, 8W DIR

For models: 15T5/HE/4F/xxx/DIR, 12T5/HE/3F/xxx/DIR, 8T5/HE/2F/xxx/DIR  
Where xxx means 824-965 which indicates CRI and color temperature

## Emergency Ballast Compatibility

Brand	Model	Compatibility		
		15T5/HE/4F/DIR	12T5/HE/3F/DIR	8T5/HE/2F/835/DIR
Bodine	B30ST	OK	OK	OK
Bodine	B50	OK	OK	OK
Bodine	B54	OK	OK	X
Bodine	B60	OK	OK	X
Bodine	B100	X	X	X
Bodine	LP550	OK	X	X
Bodine	LP600	OK	X	X
Iota	I-42-EM-R-J	OK	X	X
Iota	I-320	OK	OK	OK
Iota	ICE-80	X	OK	OK
Iota	I-232	OK	OK	OK
Iota	I-32	OK	OK	OK
Iota	ISL-54	OK	X	X
Iota	ISL-540	OK	X	X
Iota	ISD-80	OK	X	X
Lithonia	EI500	OK	X	X
Lithonia	PSQ500QD	X	X	X
Lithonia	PS1400QD	OK	OK	OK
Fulham	FH4-DUAL-700L	X	OK	X
Fulham	FH3-DUAL-450	X	X	X
Fulham	FH5-DUAL-1400L	OK	OK	OK
ALP	EFP 32GS	X	X	X

**\*GREEN CREATIVE has provided this emergency ballast compatibility chart for guidance when selecting an emergency ballast and lamp combination. Lamps were tested for compatibility with the above listed emergency ballasts. Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above emergency ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.**