



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: Reflectors Dimmable: BR30
Item Number: 772833 772834 **772835**
Ordering Code: LED12BR30/827/D/3 LED12BR30/830/D/3 **LED12BR30/840/D/3**

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes
					Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Peak hum at medium, dims down to 10%
		SureSlide	6633-P	Good	1	6	Peak hum at medium, dims down to 5%
		Vizia	VPI06-1LZ	Good	2+	6	Minor hum, dims down to 10%
	Lutron	Toggler	TG-600	Good	1	6	Minor hum, dims down to 3%
		Diva	DV-600	Good	1	6	Minor hum, dims down to 3%
		Skylark	S-600	Good	1	6	Minor hum, dims down to 3%
		Maestro	MAW-600	Bad	1	6	Flickering at high with 3, dims down to 1%
	Legrand	Titan	CD703-PW	Bad	1+	6	Flickering at high and medium with 1, dims down to 10%
		Harmony	D703-PTC	Good	1	6	Flickering at high and medium with 1, peak hum at medium, dims down to 3%
		Harmony	H703-PTC	Good	1	6	Flickering at high and medium with 1, peak hum at medium, dims down to 6%
CFL/LED	Leviton	IllumaTech	IPL06	Good	1	6	Humming full range at B, dims down to 2%
		Sureslide	6674	Good	1	6	Humming full range at B, dims down to 10%
		Decora	6672	Good	1	6	Humming full range at B, dims down to 10%
	Lutron	Skylark	CTCL-153	Good	1	6	Minor hum full range, peak hum at medium, dims down to 1%
		Diva	DVCL-153PL	Good	1	6	Minor hum full range, peak hum at medium, dims down to 1%
		Maestro	MACL-153MLH	Good	1	6	Minor hum full range, peak hum at medium, dims down to 10%
		Skylark	SCL-153P	Good	1	6	Minor hum full range, peak hum at medium, dims down to 5%
		Toggler	TGCL-153PH	Good	1	6	Minor hum full range, peak hum at medium, dims down to 1%
		Radio RA	RA2RR-6CL-PD	Good	1	6	Minor hum full range, peak hum at medium, dims down to 10%
	Legrand	Harmony	DCL453-PTC	Good	1	6	Minor hum full range, peak hum at medium, dims down to 10%
		Harmony	HCL453PTC	Good	1	6	Minor hum full range, peak hum at medium, dims down to 20%
		Adorne Paddle	ADPD453LM2	Good	1	6	Minor hum full range, peak hum at medium, dims down to 20%
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Flickering at LE with 1-6, very low hum, dims down to 10%
		IllumaTech	IPE04	Good	1	6	Flickering at LE with 1-6, very low hum, dims down to 10%
		Decora	6615-P	Good	1	6	Very low hum, dims down to 25%
	Lutron	Skylark Countour	CTELV-303P	Good	1	6	Flickering at LE with 1-6, very low hum, dims down to 10%
		Diva	DVELV-300P	Good	1	6	Flickering at LE with 1-6, very low hum, dims down to 10%
		Maestro	MAELV-600	Good	1	6	Flickering at LE with 1-6, very low hum, dims down to 10%
		Skylark	SELVB-300P	Good	1	6	Flickering at LE with 1-6, very low hum, dims down to 10%
	Legrand	VIERTI	VTEL-600M-W	Good	1	6	Very low hum, dims down to 10%
	Scene Director	SCELV	Good	1	6	Very low hum, dims down to 20%	
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2+	6	Full range hum, dims down to 10%
		Decora	6613-P	Good	1	6	Full range hum, peak hum at medium, dims down to 10%
	Lutron	Maestro	MALV-600	Not Compatible	1	6	Does not turn on with 1-6
		Harmony	DLV703-PW	Good	1	6	Flickering at high with 1, full range hum, dims down to 5%
Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 15%	
Universal	Legrand	Adorne SofTap	ADTP703TU	Good	1	6	Full range hum, dims down to 15%
		Miro Decorator	DRD4-W	Not Compatible	1	6	Strobe 1-6
		Harmony	H703PTUTC	Good	1	6	Full range hum, dims down to 20%
		Adorne Whisper	ADWR700MMTUW2	Good	1	6	Full range hum, dims down to 2%
		Adorne Touch	ADTH700MMTUM2	Good	1	6	Full range hum at B, dims down to 10%
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Full range hum, peak hum at medium, dims down to 15%
	Skye	SAL06P-W-K-L	Bad	1	6	Flickering at LE with 1-6, full range hum, peak at medium, dims down to 5%	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	