



## Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	Reflectors Value Pack Dimmable			
<b>Item Number:</b>	773350	773351	773352	773353
<b>Ordering Code:</b>	LED9BR30/827/4PK	LED9BR30/827/4PK	LED9BR30/830/4PK	LED9BR30/840/4PK

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes
					Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IP106	Good	1	6	Minor hum , dims down to 15%
		SureSlide	6633-P	Good	1	6	Minor hum , dims down to 10%
		Vizia	VPI06-1LZ	Good	1	6	1 + minimum load , minor hum , dims down to 10%
	Lutron	Toggler	TG-600	Good	1	6	Minor hum , dims down to 20%
		Diva	DV-600	Good	1	6	Minor hum , dims down to 5%
		Skylark	S-600	Good	1	6	Minor hum , dims down to 10%
		Maestro	MAW-600	Bad	1	6	Minor hum , 2 + minimum load , dims down to 5%
	Legrand	Titan	CD703-PW	Good	1	6	Dims down to 20% , minor hum
		Titan	CDLV703-PW	Best	1	6	Dims down to 20% , minor hum
		Harmony	D703-PW	Best	1	6	Dims down to 6% , minor hum
Harmony	H703-PTC	Best	1	6	Dims down to 10% , minor hum		
CFL/LED	Leviton	IllumaTech	IPL06	Good	1	6	Minor hum , dims down to 5%
		Sureslide	6674	Good	1	6	Minor hum , dims down to 15%
		Decora	6672	Good	1	6	Minor hum , dims down to 15%
	Lutron	Diva	DVCL-153PL	Good	1	6	Minor hum , dims down to 5%
		Toggler	TGCL-153PH	Good	1	6	Minor hum , dims down down to 5%
		Maestro	MACL-153MLH	Good	1	6	Minor hum , dims down to 5%
		Skylark	CTCL-153	Good	1	6	Minor hum , dims down to 5%
		Skylark	SCL-153P	Good	1	6	Minor hum , dims down to 5%
	Legrand	Radio	RA2RR-6CL-PD	Good	1	6	Minor hum , dims down to 10%
		Harmony	DCL453-PTC	Good	1	6	Dims down to 10% , minor hum
Harmony		HCL453PTC	Good	1	6	Dims down to 15%	
Adorne Paddle	ADPD453LW2	N/A					
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 15%
		IllumaTech	IPE04	Good	1	6	Steppy dimming at LE , dims down to 15%
		Decora	6615-P	Bad	1	6	Dims down to 40%
	Lutron	Skylark	SELVB-300P	Best	1	6	Dims down to 10%
		Skylark Countour	CTELV-300P	Best	1	6	Dims down to 10%
		Diva	DVELV-300P	Best	1	6	Dims down to 10%
		Maestro	MAELV-600	Best	1	6	Dims down to 4%
	Legrand	VIERTI	VTELV-600M-W	Best	1	6	Dims down to 12%
Scene Director	SCELV300	Good	1	6	Dims down to 25%		
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	1 + minimum load , minor hum , dims down to 10%
		Decora	6613-P	Good	1	6	Minor hum , dims down to 10%
	Lutron	Maestro	MALV-600	Bad	1	6	Dims down to 10% , 5+ minimum load
Legrand	Harmony	DLV703-PW	Best	1	6	Dims down to 6% , minor hum	
Universal	Legrand	Adorne SofTap	ADTP703TU	Good	1	6	Dims down to 15% , minor hum
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 10% , minor hum
		Harmony	H703PTUTC	Bad	1	6	Dims down to 30% , minor hum
		Adorne Whisper	ADWR700MMTUW2	Good	1	6	Dims down to 2% , minor hum
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 10% , minor hum
	Cooper	Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 10% , minor hum
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 5% , minor hum

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	