



# Transformer Compatibility - *Initial*

Not all transformers are compatible with LED lamps.  
TCP highly recommends that all installations be tested with samples prior to full scale installation.



Brand	Model	Input	Type	Power Rating	Number of Units					
					1	2	3	4	5	6
Advance	71A9743	120V	M	75W	Compatible					
Hatch	RS12-60M	120V	E	60	Compatible					
	RS12-80M	120V	E	80	Compatible					
	RS12-15M-LED	120V	E	15	Compatible					
	RS12-30M-LED	120V	E	30	Compatible					
	RS12-105	120V	E	105	Compatible					
Lightech	PS12-20L	120V	E	20	Compatible					
	LET 60	120V	E	60	Compatible					
Top Star	LET75	120V	E	75	Compatible					
	SL-518	120V	E	20 - 75	Compatible					
EverSale	SL-728	120V	E	20 - 105	Compatible					
	T-D12060-A	120V	E	60	Compatible					
WAC Lighting	T-D12105-A	120V	E	105	Compatible					
	EN-12100-R-AR	120V	E	35 - 100	Compatible					
	EN-1260-AR	120V	E	20 - 60	In-Compatible		Compatible			



# Transformer / Dimmer Compatibility *Initial*

## Dimming Compatibility - Electronic Transformers

					Lutron Nova NELV-450						Lutron Diva DVELV-300						Lutron Skylark SELV-300P						Lutron Leviton Sureslide 6615P					
					MR16s per Transformer						MR16s per Transformer						MR16s per Transformer						MR16s per Transformer					
Brand	Model	Input	Type	Power Rating	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6
Hatch	RS12-60M	120V	E	60	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
	RS12-80M	120V	E	80	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
	RS12-15M-LED	120V	E	15	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
	RS12-30M-LED	120V	E	30	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
Lightech	RS12-105	120V	E	105	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
	LET 60	120V	E	60	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
Top Star	LET75	120V	E	75	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
	SL-518	120V	E	20 - 75	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
EverSale	SL-728	120V	E	20-105	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
	T-D12060-A	120V	E	60	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
WAC Lighting	T-D12105-A	120V	E	105	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		
	EN-12100-R-AR	120V	E	35 - 100	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		

## Dimming Compatibility - Magnetic Transformers

					Lutron Nova NLV-600						Lutron Diva DVLV-600P						Lutron Skylark SLV-600P						Lutron Maestro MALV-600					
					MR16s per Transformer						MR16s per Transformer						MR16s per Transformer						MR16s per Transformer					
Brand	Model	Input	Type	Power Rating	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6
Advance	71A9743	120V	M	75W	1	2	3	4			1	2	3	4			1	2	3	4			1	2	3	4		

Key:

	Compatible: Very good dimming
	Compatible: Very good dimming although flicker at very bottom
	Incompatible

Not all transformers are compatible with LED lamps. TCP highly recommends that all installations be tested with samples prior to full scale installation.