













Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

**Product Family Name:** Filaments: Title 24 Compliant

776676 776677 Item Number: LED4B11/30K/FIL/E12/2/JA8 Ordering Code: LED4B11/27K/FIL/E12/2/JA8

Lamps per Dimmer

						i Dillillei	
	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
	- Walland Cure	IllumaTech	IPI06	Good	1	6	Minor flicker with 1, shimmering at high with 1-6, dims down to 1%
	Leviton	SureSlide	6633-P	Good	1	6	Minor flicker with 1, shimmering at high with 1-6, dims down to 1%
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)		Vizia	VPI06-1LZ	Good	1	6	Minor flicker at LE to Med with 1, shimmering at HE with 1-6, dims down to 1%
	Lutron	Toggler	TG-600	Good	1	6	Minor flicker at LE with 1, shimmering at HE with 1-6, dims down to 1%
		Diva	DV-600	Good	1	6	Minor flicker at LE with 1, shimmering at HE with 1-6, dims down to 1%
		Skylark	S-600	Good	1	6	Minor flicker at LE with 1, shimmering at HE with 1-6, dims down to 1%
		Maestro	MAW-600	Bad	3+	6	Shimmering at HE with 4-6, dims down to 1%
	Legrand	Titan	CD703-PW	Good	1	6	Flicker at Med with 1, minor flicker at LE with 1-6, shimmering at HE with 1-6, dims down to 1%
		Harmony	D703-PTC	Good	1	6	Flicker at Med with 1, shimmering at HE with 1-6, dims down to 1%
		Harmony	H703-PTC	Good	1	6	Flicker at Med with 1, dims down to 1%
		Tital mony	11703 1 10	2000	-	0	There at the with 1, and a dwift to 170
		IllumaTech	IPL06	Best	1 1	6	Dims down to 1%
	Leviton	Sureslide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%  Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
CFL/LED		Skylark	SCL-153P	Best	1	6	Dims down to 1%  Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%  Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%  Dims down to 1%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1%  Dims down to 1%
	Legrand	·	HCL453PTC		1	6	Dims down to 1%  Dims down to 1%
		Harmony Adorne Paddle	ADPD453LM2	Best Best	1	6	Dims down to 1%  Dims down to 10%
		Adome Paddie	ADPD453LIVI2	Best	1	D	Diffis down to 10%
		Vizia	VPE04	Good	1 1	6	Minor flicker at LE with 1-6, dims down to 1%
	Leviton	IllumaTech	IPE04	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%  Minor flicker at LE with 1-6, dims down to 1%
		Decora	6615-P	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%  Minor flicker at LE with 1-6, dims down to 10%
		Skylark Countour	CTELV-303P	Good	1	6	Minor flicker at Med with 1-6, dims down to 1%
Electronic Low Voltage		Diva	DVELV-300P	Good	1	6	Minor flicker at Med with 1-6, dims down to 1%  Minor flicker at Med with 1-6, dims down to 1%
Liectionic Low Voltage	Lutron	Maestro	MAELV-600	Best	1	6	Dims down to 1%
		Skylark	SELVB-300P	Good	1	6	Minor flicker at Med with 1-6, dims down to 1%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
	Legrand	Scene Director	SCELV SCELV	Good	1	6	Minor flicker at LE with 1-6, dims down to 10%
	Legianu	Scelle Director	SCELV		1	· ·	IMITION THERE AT LE WITH 1-0, UITHS GOWN to 10%
		Vizia	VPM-06	Good	1	6	Flicker at Med with 1, dims down to 1%
Magentic Low Voltage	Leviton		6613-P	Good	1	6	Flicker at Med with 1, dims down to 1%  Flicker at Med with 1, dims down to 1%
	Lutron	Decora	MALV-600		1	6	·
	Lutron	Maestro		Not Compatible	1	6	Doesn't turn on with 1-6
	ال مسمية ا	Harmony Titan	DLV703-PW CDLV703-PW	Good Bad	1	б	Flicker at Med with 1, dims down to 1%  Flicker at LE with 1-3, dims down to 1%
	Legrand	Han	CDLV703-PVV	Bau	1	В	FIICKER At LE WITH 1-3, GIRIS GOWN TO 1%
		Adorno Cofton	ADTP703TU	Doct	1	6	Dims down to 10%
that would	Legrand	Adorne SofTap		Best	1	0	
		Miro Decorator	DRD4-W	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%  Minor flicker at LE with 1-6, dims down to 10%
		Harmony	H703PTUTC	Good	1	ь	Minor flicker at LE with 1-6, dims down to 10%
Universal		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
		Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%
	<u>•</u>	Skye	SAL06P-W-K-L	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they

were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating						
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.					
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.					
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.					
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.					
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.					
Low End (L.E.) Dead Travel	Determines now much, if any, dead travel exists at the top and bottom of the diminer's range. Dead travel is when the slider can be moved without affecting the light level.					