SORAA BR30 120V - DIMMER COMPATIBILITY LIST - North America

Manufacturer	Model	MD#	Edge Trigger	BR30 Dim (%)
Crestron		DIN-1DIMU4	Т	10%
Lutron	Caseta	PD-5NE-XX	Т	12%
Lutron	Diva	DVELV-300P	Т	8%
Lutron	Diva	DVLV-600P	L	19%
Lutron	Diva	DVCL-153P	L	29%
Lutron	Grafik Eye QS	QSGR	L	3%
Lutron	Grafik Eye QS	QSGR + PHP module	Т	2%
Lutron	Maestro	MACL-153M	L	9%
Lutron	Radio RA2	RRD-6NA	Т	3%
Lutron	Skylark	SLV-600P	L	15%
Lutron	Skylark	SELV-300P	Т	8%
Lutron	Spacer	SPSELV-600	Т	12%
Marlin	Stellar	RMS 4	Т	4%

Notes:

Compatibility tests are conducted by Soraa (unless stated otherwise) only as guidance for the user

All tests are conducted under bench conditions; results may differ from test results depending on conditions at the application site

Results may vary due to variability in component choices and manufacturing processes by the dimmer manufacturer Regards compatibility tests conducted by dimmer manufacturer, please contact Soraa or the manufacturer for more details and/or reports.

%	Dims to < 20% (of the measured light output)
%	Dims to 20-30% (of the measured light output)
NC	Not compatible (or dims to >30%)
Blank cell	Not tested