

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:	Filaments: Fully Compatible Dimmable			
Item Number:	776656	776659	776660	776663
Ordering Code:	LED4B11/27K/FIL/E12/2	LED4CA10/27K/FIL/E12/2	LED4CA10/27K/FIL/E12/F/2	LED4B11/30K/FIL/E12/2
Item Number:	776664	776672	776673	
Ordering Code:	LED4CA10/30K/FIL/E12/2	LED4B11/27K/FIL/E12/F/2	LED4G16/27K/FIL/E12/2	

Lamps per Dimmer									
Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes			
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%		
		SureSlide	6633-P	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%		
		Vizia	VPI06-1LZ	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%		
	Lutron	Toggler	TG-600	Good	1	6	Shimmer at Med with 1, 2+ best dims down to 1%		
		Diva	DV-600	Good	1	6	Shimmer at Med with 1, 2+ best dims down to 1%		
		Skylark	S-600	Good	1	6	Shimmer at Med with 1, 2+ best dims down to 1%		
		Maestro	MAW-600	Bad	1	6	4+ minimum load		
	Legrand	Titan	CD703-PW	Bad	1	6	Flicker at Med 1& at LE 2-4, 5+ best, dims down to 1%		
		Titan	CDLV703-PW	Good	1	6	Minor flicker at Med 1-2, 3+ best, dims down to 1%		
		Harmony	D703-PTC	Bad	1	6	Flicker at Med to HE 1-2, 3+ best, dims down to 1%		
	Harmony	H703-PTC	Good	1	6	Flicker at Med to HE 1, 2+ best, dims down to 1%			
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 1%		
		Sureslide	6674	Best	1	6	Dims down to 1%		
		Decora	6672	Best	1	6	Dims down to 1%		
	Lutron	Diva	DVCL-153PL	Good	1	6	Minor flicker 1-2, 3+ best, dims down to 1%		
		Toggler	TGCL-153PH	Good	1	6	Minor flicker 1-2, 3+ best, dims down to 1%		
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%		
		Skylark	CTCL-153	Good	1	6	Minor flicker 1-2, 3+ best, dims down to 1%		
		Skylark	SCL-153P	Best	1	6	Dims down to 1%		
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%		
		Harmony	DCL453-PTC	Good	1	6	Minor flicker 1-2, 3+ best, dims down to 1%		
	Legrand	Harmony	HCL453PTC	Good	1	6	Minor flicker 1-2, 3+ best, dims down to 1%		
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 5%		
		Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
				IlumaTech	IPE04	Good	1	6	Minor flicker at Med 1, minor flicker at LE 1-6, dims down 1%
Decora	6615-P			Good	1	6	Minor flicker at LE & Med 1-6, dims down 15%		
Lutron	Skylark		SELVB-300P	Good	1	6	Shimmer at Med 1-6, dims down to 1%		
	Skylark Countour		CTELV-303P	Good	1	6	Shimmer at Med 1-4, dims down to 1%		
	Diva	DVELV-300P	Good	1	6	Shimmer at Med 1-2, dims down to 1%			
	Maestro	MAELV-600	Best	1	6	Dims down to 1%			
Legrand	VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%			
	Scene Director	SECELV	Good	1	6	Shimmer at LE 1-6, dims down to 1%			
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	Minor flicker at LE- Med 1-2, 3+ best, dims down to 1%		
		Decora	6613-P	Good	1	6	Minor flicker at Med 1-2, 3+ best, dims down to 1%		
	Lutron	Maestro	MALV-600	Bad	1	6	6+ minimum load, dims down to 5%		
		Legrand	Harmony	DLV703-PW	Good	1	6	Minor flicker at Med 1, 2+ best, dims down to 1%	
Universal	Legrand	Adorne SofTap	ADTP703TU	Good	1	6	Shimmer at LE 1-6, dims down to 5%		
		Miro Decorator	DRD4-W	Bad	1	6	Flicker at LE 1-6, dims down to 10%		
		Harmony	H703PTUTC	Good	1	6	Shimmer at LE 1-6, dims down to 15%		
		Adorne Whisper	ADWR700MMTUW2	Good	1	6	Shimmer at LE 1-6, dims down to 1%		
		Adorne Touch	ADTH700MMTUM2	Good	1	6	Shimmer at LE 1-6, dims down to 1%		
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at LE 1-6, dims down to 5%		
		Skye	SAL06P-W-K-L	Good	1	6	Minor flicker at LE 1-6, dims down to 5%		

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	