



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: Filaments: Title 24 Compliant
Item Number: 776676
Ordering Code: LED4B11/30K/FIL/E12/2/JA8 LED4B11/27K/FIL/E12/2/JA8

Lamps per Dimmer

| | Manufacturer | Product | Model Number | Overall Rating | Recommended | | Notes |
|---|--------------|------------------|----------------|----------------|-------------|---|---|
| | | | | | Minimum | Maximum Tested* | |
| Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers) | Leviton | IlumaTech | IPI06 | Good | 1 | 6 | Minor flicker with 1, shimmering at high with 1-6, dims down to 1% |
| | | SureSlide | 6633-P | Good | 1 | 6 | Minor flicker with 1, shimmering at high with 1-6, dims down to 1% |
| | | Vizia | VPI06-1LZ | Good | 1 | 6 | Minor flicker at LE to Med with 1, shimmering at HE with 1-6, dims down to 1% |
| | Lutron | Toggler | TG-600 | Good | 1 | 6 | Minor flicker at LE with 1, shimmering at HE with 1-6, dims down to 1% |
| | | Diva | DV-600 | Good | 1 | 6 | Minor flicker at LE with 1, shimmering at HE with 1-6, dims down to 1% |
| | | SkyLark | S-600 | Good | 1 | 6 | Minor flicker at LE with 1, shimmering at HE with 1-6, dims down to 1% |
| | | Maestro | MAW-600 | Bad | 3+ | 6 | Shimmering at HE with 4-6, dims down to 1% |
| | Legrand | Titan | CD703-PW | Good | 1 | 6 | Flicker at Med with 1, minor flicker at LE with 1-6, shimmering at HE with 1-6, dims down to 1% |
| | | Harmony | D703-PTC | Good | 1 | 6 | Flicker at Med with 1, shimmering at HE with 1-6, dims down to 1% |
| | | Harmony | H703-PTC | Good | 1 | 6 | Flicker at Med with 1, dims down to 1% |
| CFL/LED | Leviton | IlumaTech | IPL06 | Best | 1 | 6 | Dims down to 1% |
| | | Sureslide | 6674 | Best | 1 | 6 | Dims down to 1% |
| | | Decora | 6672 | Best | 1 | 6 | Dims down to 1% |
| | Lutron | SkyLark | CTCL-153 | Best | 1 | 6 | Dims down to 1% |
| | | Diva | DVCL-153PL | Best | 1 | 6 | Dims down to 1% |
| | | Maestro | MACL-153MLH | Best | 1 | 6 | Dims down to 1% |
| | | SkyLark | SCL-153P | Best | 1 | 6 | Dims down to 1% |
| | | Toggler | TGCL-153PH | Best | 1 | 6 | Dims down to 1% |
| | | Radio RA | RA2RR-6CL-PD | Best | 1 | 6 | Dims down to 1% |
| | Legrand | Harmony | DCL453-PTC | Best | 1 | 6 | Dims down to 1% |
| | | Harmony | HCL453PTC | Best | 1 | 6 | Dims down to 1% |
| | | Adorne Paddle | ADPP453LM2 | Best | 1 | 6 | Dims down to 10% |
| Electronic Low Voltage | Leviton | Vizia | VPED4 | Good | 1 | 6 | Minor flicker at LE with 1-6, dims down to 1% |
| | | IlumaTech | IPE04 | Good | 1 | 6 | Minor flicker at LE with 1-6, dims down to 1% |
| | | Decora | 6615-P | Good | 1 | 6 | Minor flicker at LE with 1-6, dims down to 10% |
| | Lutron | SkyLark Countour | CTELV-303P | Good | 1 | 6 | Minor flicker at Med with 1-6, dims down to 1% |
| | | Diva | DVELV-300P | Good | 1 | 6 | Minor flicker at Med with 1-6, dims down to 1% |
| | | Maestro | MAELV-600 | Best | 1 | 6 | Dims down to 1% |
| | | SkyLark | SELVB-300P | Good | 1 | 6 | Minor flicker at Med with 1-6, dims down to 1% |
| | | VIERTI | VTEL-600M-W | Best | 1 | 6 | Dims down to 1% |
| | | Scene Director | SECELV | Good | 1 | 6 | Minor flicker at LE with 1-6, dims down to 10% |
| Magnetic Low Voltage | Leviton | Vizia | VPM-06 | Good | 1 | 6 | Flicker at Med with 1, dims down to 1% |
| | | Decora | 6613-P | Good | 1 | 6 | Flicker at Med with 1, dims down to 1% |
| | Lutron | Maestro | MALV-600 | Not Compatible | 1 | 6 | Doesn't turn on with 1-6 |
| | | Harmony | DLV703-PW | Good | 1 | 6 | Flicker at Med with 1, dims down to 1% |
| Legrand | Titan | CDLV703-PW | Bad | 1 | 6 | Flicker at LE with 1-3, dims down to 1% | |
| | Universal | Legrand | Adorne SoftTap | ADTP703TU | Best | 1 | 6 |
| Miro Decorator | | | DRD4-W | Good | 1 | 6 | Minor flicker at LE with 1-6, dims down to 1% |
| Harmony | | | H703PTUTC | Good | 1 | 6 | Minor flicker at LE with 1-6, dims down to 10% |
| Adorne Whisper | | | ADWR700MMTUM2 | Best | 1 | 6 | Dims down to 1% |
| Cooper | | Adorne Touch | ADTH700MMTUM2 | Best | 1 | 6 | Dims down to 1% |
| | | Decorator | DAL06P-C2-K-L | Good | 1 | 6 | Minor flicker at LE with 1-6, dims down to 1% |
| | | Skye | SAL06P-W-K-L | Good | 1 | 6 | Minor flicker at LE with 1-6, dims down to 1% |

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

| Overall Rating | |
|------------------------------------|--|
| Not Compatible | One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off. |
| Bad | One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth. |
| Good | One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise. |
| Best | Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output. |
| High End (H.E.) Dead Travel | Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level. |
| Low End (L.E.) Dead Travel | |