



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:	Filaments: Fully Compatible Dimming				
Item Number:	776572	776574	776575	776600	776601
Ordering Code:	LED5A19/27K/FIL/2	LED7A19/27K/FIL/2	LED7G25/27K/FIL/2	LED5G25/22K/FIL-NOS/2	LED5ST18/22K/FIL-NOS/2
Item Number:	776602	776605	776609	776667	
Ordering Code:	LED5A19/22K/FIL-NOS/2	LED4T14/22K/FIL-NOS/2	LED7ST18/22K/FIL-NOS/2	LED7ST18/27K/FIL/2	

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Best	1	6	Dims down to 10%
		SureSlide	6633-P	Best	1	6	Dims down to 10%
		Vizia	VPI06-1LZ	Good	1	6	2+ minimum load, minor flicker at LE 1-6, dims down to 10%
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 1%
		Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Good	1	6	2+ minimum load, dims down to 5%
	Legrand	Titan	CD703-PW	Good	1	6	Flicker at LE with 1, dims down to 15%
		Titan	CDLV703-PW	Good	1	6	Minor flicker at LE with 1, dims down to 15%
		Harmony	D703-PTC	Good	1	6	Minor flicker Med to HE with 1, dims down to 1%
		Harmony	H703-PTC	Good	1	6	Minor flicker at LE with 1, dims down to 1%
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 5%
		Decora	6672	Best	1	6	Dims down to 5%
	Lutron	Diva	DVCL-153PL	Good	1	6	Shimmer at LE with 1-6, dims down to 1%
		Toggler	TGCL-153PH	Good	1	6	Shimmer at LE with 1-6, dims down to 1%
		Maestro	MACL-153MLH	Good	1	6	Shimmer at LE with 1-6, dims down to 10%
		Skylark	CTCL-153	Good	1	6	Shimmer at LE with 1-6, dims down to 1%
		Skylark	SCL-153P	Good	1	6	Shimmer at LE with 1-6, dims down to 1%
		Radio RA	RA2RR-6CL-PD	Good	1	6	Shimmer at LE with 1-6, dims down to 1%
	Legrand	Harmony	DCL453-PTC	Good	1	6	Shimmer at LE with 1-6, dims down to 10%
Harmony		HCL453PTC	Good	1	6	Shimmer at LE with 1-6, dims down to 10%	
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 25%
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 10%
		IllumaTech	IPE04	Good	1	6	Flicker at HE with 1, dims down to 5%
		Decora	6615-P	Bad	1	6	Flicker at HE with 1, dims down to 30%
	Lutron	Skylark	SELVB-300P	Good	1	6	Flicker at HE with 1-3, dims down to 10%
		Skylark Countour	CTELV-303P	Good	1	6	Flicker at HE with 1, dims down to 10%
		Diva	DVELV-300P	Good	1	6	Flicker at HE with 1-2, dims down to 10%
		Maestro	MAELV-600	Good	1	6	Flicker at HE with 1, dims down to 10%
	Legrand	VIERTI	VTEL-600M-W	Best	1	6	Dims down to 10%
		Scene Director	SECELV	Good	1	6	Dims down to 25%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	2+ minimum load, flicker at LE 1-6, dims down to 10%
		Decora	6613-P	Best	1	6	Dims down to 5%
	Legrand	Maestro	MALV-600	Bad	1	6	4+ minimum load, dims down to 15%
		Harmony	DLV703-PW	Good	1	6	Minor flicker at MED to HE with 1, dims down to 1%
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 10%
		Miro Decorator	DRD4-W	Not Compatible	1	6	Major flicker at Med with 1-6
		Harmony	H703PTUTC	Best	1	6	Dims down to 15%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at LE with 1-6, dims down to 20%
		Skye	SAL06P-W-K-L	Bad	1	6	Flicker at Med with 1, minor flicker at LE with 2-6

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	