
Philips LED Lamps 8.5W AirFlux2





WITHOUT DIMMER									
Number of Lamps									
1	2	3	4	5	6	7	8		

Transformer			
Brand	Part #	Power [W]	Туре
натсн	RS12-60M	60	ELV
	RS12-80	80	ELV
	RS12-80-277M	80	ELV
	RS12-150	150	ELV
	RS12-15M-LED	15	ELV
	RS12-60M-LED*	60	ELV
GE / LightTech	LET 60	60	ELV
	LET-60-LW	60	ELV
	LET-75	75	ELV
	LET-75-277-R	75	ELV
Keystone	KTET-60-1-WC-F	60	ELV
	KTET-60-1-SCP-DIM-AL	60	ELV
	KTET-75-2-SCP-RJS	75	ELV
	KTET-75-1-SCP-DIM-HV-AL	75	ELV
	KTET-150-1-SCP-DIM	150	ELV
Philips	71A9743	75	MLV
	71A9833	75	MLV

KEY					
PASS	Transformer/lamp combination is compatible for the quantity of lamps indicated				
FAIL	Transformer/lamp combination is not recommended for the quantity of lamps indicated.				

(1) Transformer load is limited to 20% of the halogen rating unless other value recommended by the transformer manufacturer.

(2) Number of Lamps = (Transformer Watts x 20%)/ (Lamp Watts)
(3)Transformers designed for LED loads are not subjected to this derating rule.

 $\hbox{@ 2016 Philips Lighting Company, A Division of Philips Electronics North America}$

All rights reserved. Updated 06/01/2016



^{*}Transformer tested only to the quantity of lamps indicated. May work similarly with additional lamps.