

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer. It is not intended to be an exhaustive list of all compatible dimmers. Actual results may vary.

Product Family Name: 776678
Item Number: LED7G40/27K/FL/LE/2
Ordering Code:

Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
				Recommended Minimum	Maximum (Load*)	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech IP06	Best	1	6	Dims down to 12%
		SureSlide 6633-P	Best	1	6	Dims down to 1%
	Viola V906-1L2	Good	2	6	Dims down to 11%	
	Lutron	Tagalog TG-600	Best	1	6	Dims down to 10%
		Diva DV-600	Best	1	6	Dims down to 1%
		Skylark S-600	Best	1	6	Dims down to 1%
		Maestro MAW-600	Good	2	6	Dims down to 12%, minor flicker LE with 3-6
		Titan TD039-PW	Good	1	6	Dims down to 12%, minor flicker LE with 1
		Harmony H703-PTC	Good	1	6	Dims down to 1%, minor flicker LE with 1
	CFL/LED	Leviton	IlumaTech IP106	Best	1	6
SureSlide 8674			Best	1	6	Dims down to 10%
Decora 8672		Best	1	6	Dims down to 5%	
Lutron		Skylark Countour CTEL-153	Best	1	6	Dims down to 1%, minor flicker below 20%, adjust ing LE above 20% avoid flicker
		Diva DWCL-153PL	Best	1	6	Dims down to 1%, minor flicker below 20%, adjust ing LE above 20% avoid flicker
		Maestro MACL-153MLH	Best	1	6	Dims down to 10%, minor flicker below 20%, adjust ing LE above 20% avoid flicker
		Skylark SCL-153P	Best	1	6	Dims down to 1%, minor flicker below 20%, adjust ing LE above 20% avoid flicker
		Tagalog TGCL-153PH	Best	1	6	Dims down to 1%, minor flicker below 20%, adjust ing LE above 20% avoid flicker
		Radio RA RA2RR-6CL-PD	Best	1	6	Dims down to 1%, minor flicker below 20%, adjust ing LE above 20% avoid flicker
Legrand		Harmony DCL453-PTC	Good	1	6	Dims down to 1%, minor flicker below 25%, adjust ing LE above 25% avoid flicker
	Adorne Paddle ADP0453LM2	Good	1	6	Dims down to 27%	
Electronic Low Voltage	Leviton	Viola V9V04	Best	1	6	Dims down to 10%
		IlumaTech IPF04	Best	1	6	Dims down to 8%
	Decora 6615-P	Good	1	6	Dims down to 35%	
	Lutron	Skylark Countour CTELV-303P	Best	1	6	Dims down to 10%
		Diva DVELV-303P	Best	1	6	Dims down to 10%
		Maestro MAELV-600	Best	1	6	Dims down to 10%
		Skylark SELVB-303P	Best	1	6	Dims down to 10%
		VERTI VTEL-600M-W	Best	1	6	Dims down to 25%
		Scene Director SCDLV	Good	1	6	
	Magnetic Low Voltage	Leviton Viola V9M-06	Good	2	6	Dims down to 7%, flicker at LE with 2
Decora 6613-P		Best	1	6	Dims down to 3%	
Lutron Maestro MALV-600		Good	2	6	Dims down to 12% with 2-6	
Legrand Harmony DLV703-PW		Best	1	6	Dims down to 3%	
Smart Dimmer	Titan CDLV703-PW	Good	1	6	Dims down to 1%, minor flicker at LE with 1	
	Leviton Decora Digital (Bluetooth) DDMX1-8L2	Good	1	6	Dims down to 13%, minor flicker at LE with 2-6	
	Leviton Decora Smart Wi-Fi DMXD-18Z	N/A				
	Lutron SwitchUp Remote Control Dimmer	N/A				
	Legrand Caseta Wireless smart dimmer Wi-Fi PD-6WCL	Good	1	6	Dims down to 6%, minor flicker at LE with 1-6	
GE	Lutron Adorne touch Wi-Fi TRU Universal ADH700RMTUW1	N/A				
	Legrand Adorne Soft Tap Wi-Fi TRU Universal ADP700RMTUW1	N/A				
Universal	GE Z-WAVE ZW300S	Good	1	6	Dims down to 5%, minor flicker at LE with 1-6	
	Legrand	Adorne SoftTap ADTP703TU	Good	1	6	Dims down to 15%, minor flicker at LE with 1-6
		Miro Decorator DRD4-W	Not Compatible	1	6	Flash at LE with 1-6
		Harmony HD303P/LTC	Good	1	6	Dims down to 15%, minor flicker at LE with 1-6
		Adorne Whisper ADWR700M/TUW2	Good	1	6	Dims down to 15%, minor flicker at LE with 1-6
		Adorne Touch ADTH700M/TUW2	Good	1	6	Dims down to 15%, minor flicker at LE with 1-6
		Decorator DAL09P-C2-K-L	Best	1	6	Dims down to 1%
	Cooper	Skay SAL09P-W-K-L	Good	1	6	Dims down to 1%, adjusting LE above 20% avoid flicker

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
May experience "pop-on": lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.