D+LIGHTING



MR16 7W 420LM 2700K GU5.3 10D MODEL SKU SE-350.001

		DIM	MER COMPA	TIBILITY LIS	Т			
	BRAND	DIMMER MODEL_TRANSFORMER	COMPATIBILITY					
MANUFACTURER			LIGHTECH LET- 60	HATCH RS12- 60M	HATCH RS12- 60M-LED	LIGHTECHINC LET 75	Trancil - THLED 50W (MAGNETIC)	MAGNETIC TRANSFORMER
LUTRON	VIVE	MRF2S-6CL-WH	OK	NC	NC	-	=	OK
	CASETA	PD-6WCL-WH	OK	NC	NC	-	=	OK
	DIVA	DV-600P-WH	-	-	-	-	-	OK
		DVELV-300P-WH	OK	OK	OK	OK	OK	OK
		DVSCCL-153P	OK	OK	NC	-	OK	-
	DIVA C*L	DVWCL-153PH-WH	-	-	-	-	-	OK
	MAESTRO	MACL-153M-WH	OK	OK	NC	-	OK	OK
		MAELV-600-WH	-	-	-	-	-	OK
		MRF2-3LD	OK	OK	OK	OK	OK	-
	SKYLARK	S-603P-WH	-	-	-	-	-	OK
		SCL-153P-WH	OK	OK	NC	OK	OK	OK
		SELV-300P-WH	-	-	-	-	-	OK
		SLV-600-WH	-	-	-	-	-	OK
		CTCL-153P	OK	OK	NC	-	OK	-
		SLV-600P	=	OK	NC	-	=	-
	SPACER	SPSELV-600M	-	-	-	-	-	OK
	NOVA T	NTELV-300-WH	-	-	-	-	-	OK
		NTLV-600-277-WH	-	-	-	-	-	OK
	RADIO RA2	RRD-6CL-WH	OK	NC	NC	-	OK	OK
		RRD-H6BRL	-	NC	NC	-	-	-
		RD-RD	-	NC	NC	-	-	_
	ARIADNI	AYCL-153P-WH	-	-	-	-	-	NG
	TOGGLER	TG-600PR	OK	OK	NC	-	NC	-
	GRAKIF EYE	-	-	OK	NC	-	-	-
	INOVAT	NTELV-300	-	OK	OK	-	-	_
	GRAPHIKG EYE OS	OSGRJ-6P	OK	OK	NC	-	OK	-
LEVITON	-	6602-IW	OK	OK	OK	-	NC	-
	=	L20-6602	-	NC	NC	-	-	-
LEGRAND	PASS & SEYMOUR	DDH16PWV	NC	NC	NC	-	NC	-
COOPER	COOPER	Aspire	NC	NC	NC	-	NC	-
LUTRON	CREDENZA	TTCL-100	NC	NC	NC	-	NC	-

DIMMER COMPATIBILITY

OK	Dims to < 15%				
OK	Dims to 15 - 30%				
NC	Not Compatible				

90+ LIGHTING NOTES

1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.

2) The results may be different for each application depending on the installation conditions.

3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.

4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.

For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

