



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

| | | | | | | | | | | | |
|-----------------------------|-------------------------------|------------------------|-----------------------|------------------------|-----------------------|-----------------------|-----------------------|------------------------|-----------------------|-----------------------|--|
| Product Family Name: | MRs Dimmable & Enclosed Rated | | | | | | | | | | |
| Item Number: | 771301 | 771302 | 771303 | 771304 | 771305 | 771306 | 771307 | 771308 | 771309 | 771310 | |
| Ordering Code: | LED8MR16SP15/50/827/D | LED8MR16NF25/50/827/D | LED8MR16FL35/50/827/D | LED8MR16WFL50/50/827/D | LED8MR16SP15/50/830/D | LED8MR16NF25/50/830/D | LED8MR16FL35/50/830/D | LED8MR16WFL50/50/830/D | LED8MR16NF25/50/850/D | LED8MR16FL35/50/850/D | |
| Item Number: | 771312 | 771313 | 771316 | 771317 | 771321 | 771322 | 771323 | 771324 | 771325 | 771326 | |
| Ordering Code: | LED8MR16NF25/50/927/D | LED8MR16FL35/50/927/D | LED8MR16NF25/50/930/D | LED8MR16FL35/50/930/D | LED9MR16SP15/75/827/D | LED9MR16NF25/75/827/D | LED9MR16FL35/75/827/D | LED9MR16WFL50/75/827/D | LED9MR16SP15/75/830/D | LED9MR16NF25/75/830/D | |
| Item Number: | 771327 | 771328 | 771332 | 771333 | 771336 | 771337 | | | | | |
| Ordering Code: | LED9MR16FL35/75/830/D | LED9MR16WFL50/75/830/D | LED9MR16NF25/75/927/D | LED9MR16FL35/75/927/D | LED9MR16NF25/75/930/D | LED9MR16FL35/75/930/D | | | | | |

| DIMMERS | | Lutron DIVA DVELV-300P | Lutron Skylark SELV-300P | Lutron Contour CTELV-300 | Lutron Vienti VTELV-600M-W | Lutron Maestro MAELV-600 | Leviton Illumatech IPE04 | Leviton Sureslide 6615 - POW | Leviton Vizilia VPE04-1LZ | Legrand Adorne ADTP703TUW4 | Legrand Adorne ADTH700MMTUW2 | |
|--------------|-----------------------|---------------------------|-----------------------------|-----------------------------|-------------------------------|-----------------------------|-----------------------------|---------------------------------|------------------------------|-------------------------------|---------------------------------|---------------|
| TRANSFORMERS | Hatch RS12-60M/LED | + F LE 1-2 | + F LE 1-2 | + F LE 1-2 | ✓ | + F LE 1-2 | + F LE 1-6 | + Dim 35% 1-6 | ✓ | ✓ | ✓ | |
| | Hatch RS12-60W | + F LE 1-2 | + F LE 1-2 | + F LE 1-2 | ✓ | + F LE 1-2 | + F LE 1-6 | + Dim 35% 1-6 | + F LE | ✓ | ✓ | |
| | Hatch VS12-60WD | + F LE 1-2 | + F LE 1-2 | + F LE 1-2 | ✓ | + F LE 1-2 | + F LE 1-6 | + Dim 35% 1-6 | + F LE | ✓ | ✓ | |
| | Hatch RS12-60M | + F LE 1-2 | + F LE 1-2 | + F LE 1-2 | ✓ | + F LE 1-2 | + F LE 1-6 | + Dim 35% 1-6 | + F LE | ✓ | ✓ | |
| | Hatch RS12-80M | + F LE 1-2 | + F LE 1-2 | + F LE 1-2 | ✓ | + F LE 1-2 | + F LE 1-6 | + Dim 35% 1-6 | + F LE | ✓ | ✓ | |
| | Lightech LET60LW | + F LE 1-2 | + F LE 1-2 | + F LE 1-2 | ✓ | + F LE 1-2 | + F LE 1-6 | + Dim 35% 1-6 | + F LE | ✓ | ✓ | |
| | Lightech LET75 | + F LE 1-2 | + F LE 1-2 | + F LE 1-2 | ✓ | + F LE 1-2 | + F LE 1-6 | + Dim 35% 1-6 | + F LE | ✓ | ✓ | |
| | WAC EN-1260-R2 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE 1-6 | + Dim 35% 1-6 | ✓ | ✓ | ✓ |
| | WAC EN-1260-R-AR | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE 1-6 | + Dim 35% 1-6 | ✓ | ✓ | ✓ |
| | WAC EN-1275-R-AR | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE 1-6 | + Dim 35% 1-6 | ✓ | ✓ | ✓ |
| | WAC EN-12100-R-AR | + F M 1 | + F M 1 | + F M 1 | ✓ | + F M 1 | + F LE 1-6 | + Dim 35% 1-6 | + F LE | + F LE 1-6 | + F LE 1-6 | + F LE 1-6 |
| | WAC EN-12150-R-AR | + F L 1 | + F L 1 | + F L 1 | ✓ | + F L 1 | + F LE 1-6 | + Dim 35% 1-6 | + F LE | -- 4 M L | -- 5 M L | -- 5 M L |
| | Solutions NET-1075 | + F L 1 | + F L 1 | + F L 1 | + | + F L 1 | + F L 1 | + F LE 1-6 | + Dim 35% 1-6 | + SH LE 1 | ✓ | ✓ |
| | LIF LF050C | | | | | | | + F LE 1-6 | + Dim 35% 1-6 | + F LE 1-6 | ✓ | ✓ |
| | Elco ET526 | ✓ | ✓ | ✓ | + minor F LE | ✓ | ✓ | + F LE | + minor F LE | + F LE | + F LE | ✓ |
| | Juno T537 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | Juno R701 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | Juno R731 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | Nora NTL-207 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | Nora NTLE-207 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | WAC-CI HHT-802 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | WAC-CI HHT-809 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | WAC-CI HHT-826 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | WAC-CI HHT-856 | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | + F LE | + Dim 35% | ✓ | ✓ | ✓ |
| | WAC W-070 | + F LE | + F LE | + F LE | + F LE | + F LE | + F LE | + F LE | + Dim 35% | + F LE | + F LE | + F LE |
| | WAC HHT-802 | NC | NC | NC | NC | NC | NC | NC | NC | NC | NC | NC |

| Overall Rating | |
|----------------|---|
| ✓ | Dims Down ≤ 20% (no flickering, no audible noise, wide dimming range) |
| + | Min 2 lamps: Dims Down ≤ 20% (minimal adjustment may be required, dead travel exists, minor audible noise) |
| + - | Min 3 lamps: Dims Down ≤ 20% (flickering observed, steppy dimming appears, voltage reverse, audible noise may be present) |
| NC | Not Compatible (major flickering observed, audible noise, no dimming range, does not turn off) |