

# 90+ LIGHTING



MODEL	RETROFIT DOWNLIGHT 15W 5" to 6" 1100LM 3000K E26
SKU	SE-350.064

DIMMER COMPATIBILITY LIST			
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
LUTRON	DIVA	DVCL-153P	OK
		DVELV-303P-AI	OK
		DVELC-303P-WH	OK
		DV-600P-WH	OK
		DVELV-300P-WH	OK
		603P-WH	OK
		DVSCCL-153P	OK
		DVWCL-153PH-WH	OK
		MAELV-600-WH	OK
		MAELV-600-WH	OK
	DIVA C+L	MAELV-600-WH	OK
		MAELV-600-WH	OK
	MAESTRO	MAELV-600-WH	OK
		MAELV-600-WH	OK
	MAESTRO WIRELESS	MAELV-600-WH	OK
		MAELV-600-WH	OK
	SKYLARK	CTELV-303P	OK
		CTELV-303P	OK
		SELV-300P-WH	NC
		SLV-600-WH	OK
		S-603P-WH	OK
		SLV-600P	OK
		S-600P-WH	OK
		LGCL-153P	OK
		LGCL-153PL	OK
		LGCL-153PLH-WH	OK
	-	1B3211	OK
	-	1C131I	OK
	VIVE	MRF2S-6CL-WH	OK
	CASETA	PD-6WCL-WH	OK
	SPACER	SPSELV-600M	OK
	NOVA T	NTELV-300-WH	OK
	RADIO RA2	NTELV-300-WH	OK
	RADIO RA3	NTLV-600-277-WH	OK
	ARIADNI	RRD-6CL-WH	OK
	VIERTI	RRD-6NA	OK
	-	AYCL-153P-WH	OK
	-	VTSELV-600M	OK
	-	DVWCL-153PH/jsb1-85	OK
	-	NTLV-600-WH/jsb1-88	OK
NOVA	NTLV-600-WH	OK	
TOGGLER	TG-600PR	OK	
GRAFIK EYE QS	QSGRJ-6P	OK	
INOVAT	NTELV-300	OK	
CASSETA	PD-6WCL	OK	
-	MRF2-3LDH	OK	
-	MAELV-600-WH	OK	
-	SCL-153P-WH	OK	
-	DVELV-300P-WH	OK	
LEVITON	-	6674	OK
	-	6633-P	OK
	-	52136	OK
	DECORA	R62-6674-POW	OK
	-	V47-C06579	OK
	-	6161	OK
	-	RPI06-1/jsb1-103	OK
	-	1PL06/jsb-92	OK
	-	RTD01-10Z/jsb-100	OK
	-	IPI06	OK
-	1PL06	OK	
-	RTD01-10Z	OK	
-	L20-6602	OK	
MAXXIMA	-	DMB01/6	OK
	-	DMA02	OK
FEIT	-	LGCL-153PLH-WH	OK
	-	LUTRO-S-600P-WH	OK
-	LEVITON-C20-06681-12A	OK	

DIMMER COMPATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

- 90+ LIGHTING NOTES**
- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
  - 2) The results may be different for each application depending on the installation conditions.
  - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
  - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.  
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.