



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:

Item Number: 776880
Ordering Code: LED2T6/27K/FIL/E12/3

776804
 LED2T6/22K/FIL-NOS/3

Item Number:
Ordering Code:

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes
					Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Best	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1
		SureSlide	6633-P	Best	1	6	Dims down to 0.1% with 1-6, minor flicker at HE with 1
		Vizia	VPI06-1LZ	Bad	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1 & LE with 2-4
	Lutron	Toggle	TG-600	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1-6
		Diva	DV-600	Best	1	6	Dims down to 0.1% with 1-6
		Skylark	S-600	Best	1	6	Dims down to 0.1% with 1-6
		Maestro	MAW-600	Bad	5	6	Dims down to 1% with 5-6,
	Legrand	Titan	CD703-PW	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at HE with 1-4
		Harmony	D703-PTC	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at HE with 1-4
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at HE with 1-4
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 0.1% with 1-6,
		Sureslide	6674	Best	1	6	Dims down to 0.1% with 1-6,
		Decora	6672	Best	1	6	Dims down to 0.1% with 1-6,
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 0.1% with 1-6,
		Diva	DVCL-153PL	Best	1	6	Dims down to 0.1% with 1-6,
		Maestro	MACL-153MLH	Best	1	6	Dims down to 0.1% with 1-6,
		Skylark	SCL-153P	Best	1	6	Dims down to 0.1% with 1-6,
		Toggle	TGCL-153PH	Best	1	6	Dims down to 0.1% with 1-6,
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 0.1% with 1-6,
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 0.1% with 1-6,
		Harmony	HCL453PTC	Best	1	6	Dims down to 0.1% with 1-6,
		Adorne Paddle	ADPP453LM2	Best	1	6	Dims down to 2% with 1-6,
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 0.1% with 1-6
		IllumaTech	IPE04	Best	1	6	Dims down to 0.1% with 1-6
		Decora	6615-P	Best	1	6	Dims down to 0.1% with 1-6
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 0.1% with 1-6
		Diva	DVELV-300P	Best	1	6	Dims down to 0.1% with 1-6
		Maestro	MAELV-600	Best	1	6	Dims down to 0.1% with 1-6
		Skylark	SELVB-300P	Best	1	6	Dims down to 0.1% with 1-6
		VIERTI	VTCL-600M-W	Best	1	6	Dims down to 0.1% with 1-6
		Scene Director	SCELV	Best	1	6	Dims down to 0.1% with 1-6
	Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6
Decora			6613-P	Good	1	6	Dims down to 0.1% with 1-6, Minor flicker at Med with 1
Lutron		Maestro	MALV-600	Not Compatible	5	6	Does not turn on with 1-6
		Harmony	DLV703-PW	Good	1	6	Dims down to 0.1% with 1-6, Minor flicker at Med with 1 -2
Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 0.1% with 1-6, Minor flicker at Med with 1 -4	
	Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6
Leviton		Decora Smart Wi-Fi	DX6HD-1BZ				
Insteon		SwitchLin Remote Control dimmer					
Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 1% with 1-6, minor flicker at LE with 1-6
Legrand		Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1				
Legrand		Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1				
GE		Z WAVE	ZW3005	Best	1	6	Dims down to 1% with 1-6
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	Dims down to 1% with 1-6
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1% with 1-6,
		Harmony	H703PTUC	Good	1	6	Dims down to 7% with 1-6, minor flicker at LE with 1-4
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1% with 1-6
		Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 1% with 1-6
	Cooper	Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 1% with 1-6,
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1% with 1-6

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	