

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: 776807
Item Number: LED4T9L/22K/FIL-NOS/3
Ordering Code:
Item Number:
Ordering Code:

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Good	1	6	Minor flicker at HE with 1-2, minor humming full range, dims down to 15%	
		SureSlide	6633-P	Best	1	6	Humming full range, dims down to 1%	
		Vizia	VPI06-1LZ	Good	2	6	Humming full range, dims down to 4%	
	Lutron	Taggler	TG-600	Good	1	6	Minor flicker at HE with 1-2, minor humming full range, dims down to 3%	
		Diva	DV-600	Good	1	6	Minor flicker at HE with 1-2, minor humming full range, dims down to 1%	
		SkyLark	S-600	Good	1	6	Minor flicker at HE with 1-2, minor humming full range, dims down to 11%	
	Legrand	Maestro	MAW-600	Good	2	6	Minor flicker at HE with 1-2, minor humming full range, dims down to 1%	
		Titan	CD703-PW	Good	1	6	Minor flicker at MED with 1, minor humming full range, dims down to 16%	
		Harmony	D703-PTC	Good	1	6	Minor flicker at HE with 2, minor flicker at MED with 1, minor humming full range, dims down to 1%	
	Harmony	H703-PTC	Good	1	6	Minor flicker at HE with 1-2, minor humming full range, dims down to 1%		
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 1%, humming full range	
		Sureslide	6674	Best	1	6	Dims down to 9%, humming full range	
		Decora	6672	Best	1	6	Dims down to 3%, humming full range	
	Lutron	Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 10%, humming full range	
		SkyLark	CTCL-153	Best	1	6	Dims down to 1%, humming full range	
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%, humming full range	
		Maestro	MAEL-153MLH	Best	1	6	Dims down to 3%, humming full range	
		SkyLark	SCL-153P	Best	1	6	Dims down to 1%, humming full range	
		Taggler	TGCL-153PH	Best	1	6	Dims down to 1%, humming full range	
	Legrand	Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%, humming full range	
		Harmony	DCL453-PTC	Best	1	6	Dims down to 3%, humming full range	
		Harmony	HCL453PTC	Best	1	6	Dims down to 10%, humming full range	
		Adorne Paddle	ADPD453LM2	Bad	1	6	Dims down to 36%, humming full range	
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 13%, no humming	
		IlumaTech	IPE04	Best	1	6	Dims down to 10%, no humming	
		Decora	6615-P	Bad	1	6	Dims down to 43%, no humming	
	Lutron	SkyLark Countour	CTELV-303P	Best	1	6	Dims down to 10%, no humming	
		Diva	DVELV-300P	Best	1	6	Dims down to 10%, no humming	
		Maestro	MAELV-600	Best	1	6	Dims down to 10%, no humming	
		SkyLark	SELV-300P	Best	1	6	Dims down to 10%, no humming	
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 30%, no humming	
		Scene Director	SCELV	Best	1	6		
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Minor flicker at HE with 1-2, minor humming full range, dims down to 5%	
		Decora	6613-P	Good	1	6	Minor flicker at HE with 1, minor humming full range, dims down to 1%	
	Lutron	Maestro	MALV-600	Good	3	6	Minor humming full range, dims down to 4%	
		Harmony	DLV703-PW	Good	1	6	Minor flicker at HE with 1, minor humming full range, dims down to 1%	
	Legrand	Titan	CDLV703-PW	Good	1	6	Minor flicker at MED with 1, minor humming full range, dims down to 17%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 15%, humming full range	
	Leviton	Decora Smart Z-Wave Technology	DZGHD	Best	1	6	Dims down to 10%, humming full range	
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 5%, humming full range	
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 10%, humming full range	
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1					
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1					
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%, humming full range	
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	Minor humming full range, dims down to 18%	
		Miro Decorator	DRD4-W	Good	1	6	Minor humming full range, flicker at HE 1-2, dims down to 1%	
		Harmony	H703PTUTC	Bad	1	6	Major flicker at HE with 1-6	
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%	
		Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 1%	
	Cooper	Decorator	DAL06P-CZ-K-L	Good	1	6	Minor humming full range, flicker at LE 1-6, dims down to 1%	
		Skye	SAL06P-W-K-L	Good	1	6	Minor humming full range, flicker at LE 1-6, dims down to 1%	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	