



## Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Filaments: Fully Compatible Dimming

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Min	Max*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%
		SureSlide	6633-P	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%
		Vizia	VPI06-1LZ	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%
	Lutron	Toggler	TG-600	Good	1	6	Shimmer at Med with 1, 2+ best dims down to 1%
		Diva	DV-600	Good	1	6	2+ minimum load, 3+ best dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Bad	1	6	5+ minimum load
	Legrand	Titan	CD703-PW	Bad	1	6	Flicker at HE 1-2, 4+ best, dims down to 1%
		Titan	CDLV703-PW	Bad	1	6	Flicker at Med 1-3, 4+ best, dims down to 1%
		Harmony	D703-PTC	Bad	1	6	Flicker at Med to HE 1-3, 4+ best, dims down to 1%
		Harmony	H703-PTC	Good	1	6	Flicker at Med to HE 1, 2+ best, dims down to 1%
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
	Lutron	Diva	DVCL-153PL	Good	1	6	Minor flicker 1-2, 3+ best, dims down to 1%
		Toggler	TGCL-153PH	Good	1	6	Minor flicker 1-2, 3+ best, dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		Skylark	CTCL-153	Good	1	6	Minor flicker 1-2, 3+ best, dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
Harmony		HCL453PTC	Best	1	6	Dims down to 1%	
Adorne Paddle		ADPD453LM2	Best	1	6	Dims down to 5%	
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
		IllumaTech	IPE04	Good	1	6	Minor flicker at LE 1, minor flicker at Med 1-6, dims down 1%
		Decora	6615-P	Good	1	6	Minor flicker at LE 1-6, dims down 15%
	Lutron	Skylark	SELVB-300P	Good	1	6	Shimmer at Med 1-2, dims down to 1%
		Skylark Countour	CTELV-303P	Good	1	6	Shimmer at Med 1-3, dims down to 1%
		Diva	DVELV-300P	Good	1	6	Shimmer at Med 1, dims down to 1%
		Maestro	MAELV-600	Best	1	6	Dims down to 1%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
	Legrand	Scene Director	SCELV	Best	1	6	Dims down to 1%
	Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6
Decora			6613-P	Good	1	6	Minor flicker at Med 1-2, 3+ best, dims down to 1%
Lutron		Maestro	MALV-600	Bad	1	6	5+ minimum load, dims down to 5%
Legrand		Harmony	DLV703-PW	Good	1	6	Minor flicker at Med 1, 2+ best, dims down to 1%
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 1%
		Miro Decorator	DRD4-W	Good	1	6	Minor flicker at LE 1-3
		Harmony	H703PTUTC	Best	1	6	Dims down to 10%
		Adorne Whisper	ADWR700MMTUM2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at LE 1-6, dims down to 5%
		Skye	SAL06P-W-K-L	Good	1	6	Minor flicker at LE 1-6, dims down to 5%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	