



## Recommended Dimmers for Cree® PRO Series PAR38 120W LED Bulbs.

CREES

Cree PRO Series LED bulbs are designed to be dimmed with standard incandescent type dimmers and are compatible with most Electric Low Voltage (ELV) dimmers. This list was generated from lab testing of samples and your results may vary.\*

## **Works Best With**

No flickering or shimmer observed and smooth dimming across range. No audible noise.

	Part	Phase	Rating	Bulbs Per Dimmer	
Manufacturer	Number	Cut Edge	(W)	min	max
Leviton	6633	Leading	600	1	7
Leviton	6672	Leading	600/150	1	7
Leviton	6674	Leading	600/150	1	7
Leviton	DSL-06	Leading	600/150	1	7
Leviton	IPL06	Leading	600/150	1	7
Lutron	D <b>V</b> -600P	Leading	600	1	7
Lutron	DVCL-153P	Leading	600/150	1	7
Lutron	LGCL-153	Leading	600/150	1	7
Lutron	MACL-153	Leading	600/150	1	7
Lutron	PD-6WCL	Leading	600/150	1	7
Lutron	RRD-6NA	Leading	600	1	7
Lutron	SELV-300P	Trailing	300	1	14
Lutron	TG-600PH	Leading	600	1	7

## **Works With**

May produce some flicker or shimmer.
Minimum adjustment to dimming level may be required.
No audible noise.

		Ÿ	¥	Bulbs Per Dimmer		
Manufacturer	Part Number	Phase Cut Edge	Rating (W)	min	max	
Leviton	6615	Trailing	300	4	14	
Leviton	IPE04	Trailing	300	4	14	

## **Compatible Part Numbers**



PAR38-120W-P1-27K-40FL E26-U1
PAR38-120W-P1-27K-25NF-E26-U1
PAR38-120W-P1-27K-15SP-E26-U1
PAR38-120W-P1-30K-40FL E26-U1
PAR38-120W-P1-30K-25NF-E26-U1
PAR38-120W-P1-30K-15SP-E26-U1
PAR38-120W-P1-40K-40FL E26-U1

\*The presence of a dimmer on this chart is not a guarantee or warranty of the compatibility of the LED bulb in any particular installation. Absence of a dimmer from this chart does not imply incompatibility.

Please reference the dimmer manufacturer's instructions for installation and further information.