

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:		
Item Number:	776775	776883
Ordering Code:	LED8G25/27K/FIL/3	LED/8G40/27K/FIL/M/3
Item Number:		
Ordering Code:		

Lamps per Dimmer	Manufacturer		Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes	
	Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPL06	IPL06	Best	1	6	Dims down to 18%
SureSlide				6633-P	Best	1	6	Dims down to 2%	
Vizia				VPI06-1LZ	Good	2	6	Dims down to 7%	
Lutron			Toggle	TG-600	Best	1	6	Dims down to 10%	
			Diva	DV-600	Best	1	6	Dims down to 1%	
			SkyLark	S-600	Best	1	6	Dims down to 1%	
Legrand			Maestro	MAW-600	Best	2	6	Dims down to 6%	
			Titan	CD703-PW	Best	1	6	Dims down to 20%	
			Harmony	D703-PTC	Best	1	6	Dims down to 1%	
CFL/LED		Leviton	IllumaTech	IPL06	IPL06	Best	1	6	Dims down to 2%
				Sureslide	6674	Best	1	6	Dims down to 10%
				Decora	6672	Best	1	6	Dims down to 8%
	Lutron		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 10%	
			SkyLark	CTCL-153	Best	1	6	Dims down to 1%	
			Diva	DVCL-153PL	Best	1	6	Dims down to 1%	
	Lutron		Maestro	MAEL-153MLH	Best	1	6	Dims down to 7%	
			SkyLark	SCL-153P	Best	1	6	Dims down to 1%	
			Toggle	TGCL-153PH	Best	1	6	Dims down to 1%	
	Legrand		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 5%	
			Harmony	DCL453-PTC	Best	1	6	Dims down to 7%	
			Harmony	HCL453PTC	Best	1	6	Dims down to 15%	
			Adorne Paddle	ADPD453LM2	Bad	1	6	dims down to 38%	
Electronic Low Voltage	Leviton	IllumaTech	VPE04	VPE04	Best	1	6	Dims down to 13%	
			IPE04	IPE04	Best	1	6	Dims down to 10%	
			Decora	6615-P	Bad	1	6	Dims down to 42%	
	Lutron		SkyLark Countour	CTELV-303P	Best	1	6	Dims down to 10%	
			Diva	DVELV-300P	Best	1	6	Dims down to 10%	
			Maestro	MAELV-600	Best	1	6	Dims down to 10%	
	Lutron		SkyLark	SELVB-300P	Best	1	6	Dims down to 10%	
			VIERTI	VTEL-600M-W	Best	1	6	Dims down to 10%	
			Scene Director	SCELV	Bad	1	6	Dims down to 27%	
	Magnetic Low Voltage	Leviton	Vizia	VPM-06	VPM-06	Best	2	6	Dims down to 9%
				Decora	6613-P	Best	1	6	Dims down to 4%
		Lutron		Maestro	MALV-600	Best	2	6	Dims down to 7%
Harmony				DLV703-PW	Best	1	6	Dims down to 1%	
Lutron		Titan	CDLV703-PW	Best	1	6	Dims down to 20%		
		Smart Dimmer		Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 18%
Decora Smart Z-Wave Technology	DZ6HD			Best	1	6	Dims down to 15%		
Caseta Wireless smart dimmer Wi-Fi	PD-10NXD			Best	1	6	Dims down to 13%		
Caseta Wireless smart dimmer Wi-Fi	PD-6WCL			Best	1	6	Dims down to 7%		
Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1								
Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1								
Universal	Legrand		Z WAVE	ZW3005	Best	1	6	Dims down to 1%	
			Adorne SoftTap	ADTP703TU	Good	1	6	Dims down to 24%	
			Miro Decorator	DRD4-W	Good	1	6	Dims down to 2%, shimmer at LE with 1-6	
			Harmony	H703PTUTC	Good	1	6	Dims down to 28%	
			Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 2%	
			Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 3%	
Cooper		Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6		
		Skye	SAL06P-W-K-L	Good	1	6	Dims down to 1% minor flicker at LE with 1-6		

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	