



545 West Commercial Ave.  
Masonville, TN 37024

### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	PAR3-PREFERRED SERIES	PAR30 SHORT NECK & LONG NECK		
<b>Item Number:</b>	772763	772769	772775	772779
<b>Ordering Code:</b>	LED10PAR30S/NF25/830/W/2	LED10PAR30S/NF25/830/W/2	LED10PAR30/NF25/830/W/2	LED10PAR30/NF25/830/W/2
<b>Item Number:</b>	772764	772768	772776	772780
<b>Ordering Code:</b>	LED10PAR30S/FL40/827/W/2	LED10PAR30S/FL40/830/W/2	LED10PAR30/FL40/827/W/2	LED10PAR30/FL40/830/W/2

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	Ilumatech	IP06	Best	1	6	Dims down to 1%
		SureSlide	6633-P	Best	1	6	Dims down to 1%
		Vizia	VP06-1LZ	Best	1	6	Dims down to 1%
		Toggle	TD-600	Good	1	6	Dims down to 1%, minor flicker at LE with 1-2
		Lumex	LGCL-600	Best	1	6	Dims down to 1%
	Lutron	Dival	DV-600	Good	1	6	Dims down to 1%, minor flicker at LE with 6
		Skylark	S-600	Good	1	6	Dims down to 1%, minor flicker at LE with 6
		Maestro	MAW-600	Bad	6	6	Dims down to 1% with 6 up
		Titan	TD703-PW	Bad	2	6	Dims down to 1%, flicker at Med with 2-6 and at LE with 4-6
		Harmony	D703-PTC	Good	2	6	Dims down to 1%, flicker at HE with 2
CFL/LED	Leviton	Ilumatech	IP06	Best	1	6	Dims down to 1%
		SureSlide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%
		Skylark	TKCL-153	Good	1	6	Dims down to 1%, flicker at 7% with 3-6
	Lutron	Dival	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggle	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2R-RCL-PD	Best	1	6	Dims down to 1%
Legrand	Harmony	DC453-PTC	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	Harmony	HCL453PTC	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
	Adorne Paddle	ADPD453LM2	Bad	1	6	Dims down to 1%, flicker at LE with 1-6	
Electronic Low Voltage	Leviton	Ilumatech	IPED4	Best	1	6	Dims down to 1%
		SureSlide	6674	Best	1	6	Dims down to 1%
		Decora	6615-P	Best	1	6	Dims down to 1%
		Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%
		Dival	DVELV-300P	Best	1	6	Dims down to 1%
	Lutron	Maestro	MALEV-600	Best	1	6	Dims down to 1%
		Skylark	SELV-300P	Best	1	6	Dims down to 1%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
		Scene Director	SCELV	Best	1	6	Dims down to 7%
Magnetic Low Voltage	Leviton	Vizia	VM-06	Best	1	6	Dims down to 1%
		Decora	6613-P	Good	1	6	Dims down to 1%
	Lutron	Maestro	MALV-600	Not Compatible	1	6	Not turn on with 1-6
		Harmony	DLV703-PW	Good	1	6	Dims down to 1%, minor flicker at LE with 1
		Titan	CDLV703-PW	Good	1	6	Dims down to 1%, minor flicker at LE with 2-6
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDIMX1-BLZ	Best	1	6	Dims down to 1%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%
	Leviton	Decora Smart Wi-Fi Technology	DW4KD	Best	1	6	Dims down to 5%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NKO	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 1%
	GE	Z WAVE	ZW3005	Best	1	6	
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	Dims down to 1%
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1%
		Harmony	H703PTJTC	Good	1	6	Dims down to 15%
	Cooper	Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch Decorator	ADTW700MMTUW2	Best	1	6	Dims down to 1%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.  
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

<b>Overall Rating</b>	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	

Contact information:  
 Bulbrite Industries Inc.  
 545 West Commercial Avenue  
 Masonville, New Jersey 07074  
 PHONE: 1-800-528-5555  
 FAX: 1-800-443-7728  
 Email: ProductSupport@Bulbrite.com  
 ©2017 Bulbrite Industries Inc.  
 All Rights Reserved.