



345 West Commercial Ave.
Lansing, MI 48204

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility data is based on testing conducted by the manufacturer in a lab environment. Actual results may vary.

Product Family Name:	772787	772788	772791	772792
Item Number:	LED15PAR38/NF25/827/WD/2	LED15PAR38/FL40/827/WD/2	LED15PAR38/NF25/830/WD/2	LED15PAR38/FL40/830/WD/2
Ordering Code:				
Item Number:				
Ordering Code:				

Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
				Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech IP06	Best	1	6	Dims down to 1%
		SureSlide 6633-P	Best	1	6	Dims down to 1%
		Vizia VP06-1L2	Good	1	6	Dims down to 1%, flicker at LE with 1
	Lutron	Topgler TG-400	Good	1	6	Dims down to 2%, minor flicker at LE with 1-6
		Lumea LGCL-600	Best	1	6	Dims down to 1%
		Diva DV-600	Best	1	6	Dims down to 1%
		SkyLark SKL-600	Best	1	6	Dims down to 1%
		Maestro MAW-600	Good	3	6	Dims down to 1%, flicker at LE with 3-6
		Titan CD703-PW	Bad	1	6	Dims down to 2%, flicker at HE & LE with 1, flicker at LE with 2-6
		Harmony D703-PTC	Good	2	6	Dims down to 1%
Legrand H703-PTC	Good	2	6	Dims down to 1%		
CFL/LED	Leviton	IlumaTech IPL06	Best	1	6	Dims down to 1%
		SureSlide 6674	Best	1	6	Dims down to 1%
		Decora 6672	Best	1	6	Dims down to 1%
	Lutron	Decora Slide DSLO6-1L2	Best	1	6	Dims down to 1%
		SkyLark CTCL-153	Best	1	6	Dims down to 1%
		Diva DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro MACL-153MLH	Best	1	6	Dims down to 1%
		SkyLark SCL-153P	Best	1	6	Dims down to 1%
		Topgler TGCL-153PH	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
		Radio RA RAR38-4CL-PO	Best	1	6	Dims down to 1%
Legrand	Harmony DCL453-PTC	Best	1	6	Dims down to 1%	
	Harmony HCL453PTC	Best	1	6	Dims down to 1%	
	Adorne Paddle ADPD453LM2	Best	1	6	Dims down to 1%	
Electronic Low Voltage	Leviton	Vizia VPE04	Best	1	6	Dims down to 1%
		IlumaTech IPE04	Best	1	6	Dims down to 1%
	Lutron	Decora 6615-P	Best	1	6	Dims down to 8%
		SkyLark Countour CTCLV-303P	Best	1	6	Dims down to 1%
		Diva DVELV-300P	Best	1	6	Dims down to 1%
		Maestro MALLV-600	Best	1	6	Dims down to 1%
Legrand	SkyLark SELV8-300P	Best	1	6	Dims down to 1%	
	VIERTI VTEL-600M-W	Best	1	6	Dims down to 1%	
Magnetic Low Voltage	Leviton	Vizia VPM-06	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
		Decora 6613-P	Best	1	6	Dims down to 1%
	Lutron	Maestro MALV-600	Not Compatible	1	6	Not turn on with 1-6
		Harmony DVLV703-PW	Good	1	6	Dims down to 1%, flicker at LE with 1-6
Smart Dimmer	Lutron	Decora Digital (Bluetooth) DDMX1-BL2	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
		Decora Smart Z-Wave Technology DZSHD	Best	1	6	Dims down to 1%
	Lutron	Decora Smart WiFi Technology DW1KD	Best	1	6	Dims down to 1%
		Caseta Wireless smart dimmer Wi-Fi PD-10NXD	Best	1	6	Dims down to 1%
GE	Caseta Wireless smart dimmer Wi-Fi PD-6WCL	Best	1	6	Dims down to 1%	
	Z-WAVE ZW3005	Good	1	6	Dims down to 1%, minor flicker at LE with 1-6	
Universal	Legrand	Adorne SoftTap ADTP703TU	Best	1	6	Dims down to 1%
		Mino Decorator DBD4-W	Good	1	6	Dims down to 1%, minor flicker LE with 1-6
		Harmony H703PTUTC	Good	1	6	Dims down to 18%
	Cooper	Adorne Whisper ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch ADT1700MMTUW2	Best	1	6	Dims down to 1%
		Decorator DAL05P-C2-K-L	Good	1	6	Dims down to 1%, minor flicker LE with 1-6
Skye SAL06P-W-K-L	Good	1	6	Dims down to 1%, minor flicker LE with 1-6		

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise may be present.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Additional Information:
 Bulbrite Industries, Inc.
 345 West Commercial Avenue
 Lansing, Michigan 48204
 PHONE: 1-800-538-2555
 FAX: 517-484-7158
 Email: ProductSupport@bulbrite.com
 ©2017 Bulbrite Industries, Inc.
 All Rights Reserved.