



345 West Commercial Ave.
Lansing, MI 48204

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility data is based on testing conducted by the manufacturer in a lab environment. Actual results may vary.

Product Family Name:	772787	772788	772791	772792
Item Number:	LED15PAR38/NF25/827/WD/2	LED15PAR38/FL40/827/WD/2	LED15PAR38/NF25/830/WD/2	LED15PAR38/FL40/830/WD/2
Ordering Code:				
Item Number:				
Ordering Code:				

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer			Notes
					Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IP06	Best	1	6	Dimms down to 1%	
		SureSlide	6633-P	Best	1	6	Dimms down to 1%	
		Vizia	VP06-1L2	Good	1	6	Dimms down to 1%, flicker at LE with 1	
		Topgler	TG-400	Good	1	6	Dimms down to 2%, minor flicker at LE with 1-6	
		Lumea	LGCL-600	Best	1	6	Dimms down to 1%	
		Diva	DV-600	Best	1	6	Dimms down to 1%	
	Lutron	SkyLark	S-600	Best	1	6	Dimms down to 1%	
		Maestro	MAW-600	Good	3	6	Dimms down to 1%, flicker at LE with 3-6	
		Titan	CD703-PW	Bad	1	6	Dimms down to 2%, flicker at HE & LE with 1, flicker at LE with 2-6	
		Harmony	D703-PTC	Good	2	6	Dimms down to 1%	
		Harmony	H703-PTC	Good	2	6	Dimms down to 1%	
		Legrand						
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dimms down to 1%	
		SureSlide	6674	Best	1	6	Dimms down to 1%	
		Decora	6672	Best	1	6	Dimms down to 1%	
		Decora Slide	DSL06-1L2	Best	1	6	Dimms down to 1%	
		SkyLark	CTCL-153	Best	1	6	Dimms down to 1%	
		Diva	DVCL-153PL	Best	1	6	Dimms down to 1%	
	Lutron	Maestro	MACL-153MLH	Best	1	6	Dimms down to 1%	
		SkyLark	SCL-153P	Best	1	6	Dimms down to 1%	
		Topgler	TGCL-153PH	Good	1	6	Dimms down to 1%, minor flicker at LE with 1-6	
		Radio RA	RA309-4CL-PO	Best	1	6	Dimms down to 1%	
		Harmony	DCL453-PTC	Best	1	6	Dimms down to 1%	
		Harmony	HCL453PTC	Best	1	6	Dimms down to 1%	
Legrand								
Adorne Paddle	ADPD453LM2	Best	1	6	Dimms down to 1%			
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dimms down to 1%	
		IlumaTech	IPED4	Best	1	6	Dimms down to 1%	
		Decora	6615-P	Best	1	6	Dimms down to 8%	
		SkyLark Countour	CTELV-303P	Best	1	6	Dimms down to 1%	
		Diva	DVELV-300P	Best	1	6	Dimms down to 1%	
		Maestro	MALV-600	Best	1	6	Dimms down to 1%	
	Lutron	SkyLark	SELV-300P	Best	1	6	Dimms down to 1%	
		VIERTI	VTEL-600M-W	Best	1	6	Dimms down to 1%	
		Scene Director	SCELV	Best	1	6	Dimms down to 1%	
		Legrand						
		Vizia	VPM-06	Good	1	6	Dimms down to 1%, minor flicker at LE with 1-6	
		Decora	6613-P	Best	1	6	Dimms down to 1%	
Magnetic Low Voltage	Lutron	Maestro	MALV-600	Not Compatible	1	6	Not turn on with 1-6	
		Harmony	DVL703-PW	Good	1	6	Dimms down to 1%, flicker at LE with 1-6	
		Titan	CDLV703-PW	Good	1	6	Dimms down to 1%, flicker at LE with 1-6	
		Legrand						
		Decora Digital (Bluetooth)	DDMX1-BL2	Good	1	6	Dimms down to 1%, minor flicker at LE with 1-6	
		Decora Smart Z-Wave Technology	DZSHD	Best	1	6	Dimms down to 1%	
	Smart Dimmer	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dimms down to 1%	
		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dimms down to 1%	
		Caseta Wireless smart dimmer Wi-Fi	PD-SWCL	Best	1	6	Dimms down to 1%	
		Z-WAVE	ZW3005	Good	1	6	Dimms down to 1%, minor flicker at LE with 1-6	
		Legrand						
		Adorne SoftTap	ADTF703TU	Best	1	6	Dimms down to 1%	
Universal	Lutron	Mira Decorator	DRD4-W	Good	1	6	Dimms down to 1%, minor flicker LE with 1-6	
		Harmony	H703PTUTC	Good	1	6	Dimms down to 18%	
		Adorne Whisper	ADAW700MMTUW2	Best	1	6	Dimms down to 1%	
		Adorne Touch	ADTW700MMTUW2	Best	1	6	Dimms down to 1%	
		Cooper	DAL05P-C2-K-L	Good	1	6	Dimms down to 1%, minor flicker LE with 1-6	
		Skye	SAL06P-W-K-L	Good	1	6	Dimms down to 1%, minor flicker LE with 1-6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise may be present.
Best	Most of the following observed: No flickering, minimal audible noise typically less than 25 dBA, wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Additional Information:
 Bulbrite Industries, Inc.
 345 West Commercial Avenue
 Bloomhills, New Jersey 07004
 PHONE: 1-800-538-2555
 FAX: 1-800-441-7158
 Email: ProductSupport@bulbrite.com
 ©2017 Bulbrite Industries, Inc.
 All Rights Reserved.