



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:	772286	772290
Item Number:	LED10PAR30/FL40/927/WD/2	LED10PAR30/FL40/930/WD/2
Ordering Code:		
Item Number:		
Ordering Code:		

Lamps per Dimmer	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
					Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IP106	Good	1	6	Dims down to 20%	
		SureSlide	6633-P	Best	1	6	Dims down to 7%	
		Vizia	VP106-1LZ	Good	3	6	Dims down to 11%	
	Lutron	TG-600	TG-600	Good	1	6	Dims down to 14%	
		Lumina	LGCL-600	Good	1	6	Dims down to 13%	
		Divva	DV-600	Best	1	6	Dims down to 4%	
		SkyLark	S-600	Best	1	6	Dims down to 5%	
		Maestro	MAW-600	Good	3	6	Dims down to 8%	
		Titan	CD703-PW	Good	1	6	Dims down to 20%	
	Legrand	Harmony	H703-PTC	Best	1	6	Dims down to 3%	
		Harmony	H703-PTC	Good	1	6	Dims down to 8%, minor flicker at LE with 1	
	CFL/LED	Leviton	IlumaTech	IP106	Best	1	6	Dims down to 1%
SureSlide			6674	Good	1	6	Dims down to 13%	
Decora			6672	Good	1	6	Dims down to 13%	
Lutron		Decora Slide	DSL06-1LZ	Good	1	6	Dims down to 13%	
		SkyLark	CTCL-153	Best	1	6	Dims down to 2%	
		Divva	DVCL-153PL	Best	1	6	Dims down to 2%	
		Maestro	MACL-153MLH	Best	1	6	Dims down to 10%	
		SkyLark	SCL-153P	Best	1	6	Dims down to 2%	
		Toggle	TGCL-153PH	Best	1	6	Dims down to 2%	
Legrand		Radio RA	RA2R8-GCL-PD	Best	1	6	Dims down to 10%	
		Harmony	DCL453-PTC	Best	1	6	Dims down to 9%	
		Harmony	HCL453PTC	Good	1	6	Dims down to 22%	
Electronic Low Voltage	Leviton	Vizia	VPED4	Good	1	6	Dims down to 14%	
		IlumaTech	IPED4	Good	1	6	Dims down to 12%	
		Decora	6615-P	Bad	1	6	Dims down to 34%	
	Lutron	SkyLark Countour	CTELV-303P	Good	1	6	Dims down to 13%	
		Divva	DVELV-300P	Good	1	6	Dims down to 13%	
		Maestro	MAELV-400	Good	1	6	Dims down to 11%	
		SkyLark	SELVB-300P	Good	1	6	Dims down to 13%	
		VIERTI	VTEL-600M-W	Good	1	6	Dims down to 13%	
		Scene Director	SECELV	Bad	1	6	Dims down to 25%	
	Magnetic Low Voltage	Leviton	Vizia	VPMD-06	Good	3	6	Dims down to 10%
			Decora	6613-P	Best	1	6	Dims down to 7%
		Lutron	Maestro	MAVLV-600	Good	4	6	Dims down to 13%
Harmony			DLV703-PW	Good	1	6	Dims down to 3%, minor flicker at LE with 1	
Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 15%		
	Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Dims down to 14%
Leviton		Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Dims down to 14%	
Leviton		Decora Smart WiFi Technology	DW1KD	Good	1	6	Dims down to 14%	
Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dims down to 13%	
Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 11%,	
GE		Z WAVE	ZW3005	Best	1	6	Dims down to 3%	
Universal	Legrand	Adorne Soffap	ADTP703TU	Good	1	6	Dims down to 21%	
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 6%	
		Harmony	H703PTUTC	Bad	1	6	Dims down to 30%	
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 3%	
	Cooper	Adorne Touch	ADTN700MMTUW2	Best	1	6	Dims down to 3%	
		Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 2%	
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 2%	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 *May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	None of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor flickering at some point may exist.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 10% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

Contact Information:
 Bulbrite Industries Inc.
 145 West Commercial Avenue
 Moonachie, New Jersey 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708
 Email: ProductSupport@bulbrite.com
 © 2013 Bulbrite Industries Inc.
 All Rights Reserved.