



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:			
Item Number:	773230	773231	773232
Ordering Code:	LED7IBOXDL/3/927/WHRD/D	LED7IBOXDL/3/930/WHRD/D	LED7IBOXDL/3/940/WHRD/D
Item Number:			
Ordering Code:			

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum		Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IP105	Good	1	6		Dims down to 8%
		SureSlide	6633-P	Good	1	6		Dims down to 14%
		Vizia	VPI06-1LZ	Good	3	6		Dims down to 12%
	Lutron	Toggle	TG-600	Good	1	6		Dims down to 20%
		Diva	DV-600	Best	1	6		Dims down to 8%
		SkyLark	S-600	Good	1	6		Dims down to 12%
		Maestro	MAW-600	Good	2	6		Dims down to 4%
	Legrand	Titan	CD703-PW	Good	1	6		Dims down to 23%
		Harmony	D703-PTC	Best	1	6		Dims down to 8%
		Harmony	H703-PTC	Good	1	6		Dims down to 15%
CFL/LED	Leviton	IllumaTech	IP106	Best	1	6		Dims down to 1%
		Sureslide	6674	Good	1	6		Dims down to 15%
		Decora	6672	Good	1	6		Dims down to 20%
	Lutron	Decora Slide	DSL06-1LZ	Good	1	6		Dims down to 15%
		SkyLark	CTL-153	Best	1	6		Dims down to 1%
		Diva	DVCL-153PL	Best	1	6		Dims down to 1%
		Maestro	MACL-153MLH	Good	1	6		Dims down to 12%
		SkyLark	SCL-153P	Best	1	6		Dims down to 1%
		Toggle	TGCL-153PH	Best	1	6		Dims down to 1%
	Legrand	Radio RA	RA2RR-GCL-PD	Best	1	6		Dims down to 9%
		Harmony	DCL453-PTC	Best	1	6		Dims down to 10%
		Harmony	HCL453PTC	Good	1	6		Dims down to 16%
		Adorne Paddle	ADPD453LM2	Bad	1	6		Dims down to 33%
Electronic Low Voltage	Leviton	Vizia	VP604	Best	1	6		Dims down to 16%
		IllumaTech	IP604	Best	1	6		Dims down to 10%
		Decora	6615-P	Bad	1	6		Dims down to 38%
	Lutron	SkyLark Countour	CTELV-303P	Best	1	6		Dims down to 13%
		Diva	DVELV-300P	Best	1	6		Dims down to 13%
		Maestro	MAELV-600	Best	1	6		Dims down to 11%
		SkyLark	SELVB-300P	Best	1	6		Dims down to 13%
		VIERTI	VTEL-600M-W	Good	1	6		Dims down to 15%
		Scene Director	SCELV	Bad	1	6		Dims down to 27%
	Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	4	6	
Decora			6613-P	Good	1	6		Dims down to 16%
Lutron		Maestro	MALV-600	Good	2	6		Dims down to 11%
		Harmony	DLV703-PW	Best	1	6		Dims down to 10%
Legrand	Titan	CDLV703-PW	Good	1	6		Dims down to 20%	
	Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	
Leviton		Decora Smart Z-Wave Technology	DZ6HD	Good	1	6		Dims down to 17%
Leviton		Decora Smart Wi-Fi Technology	DW1KD	Good	1	6		Dims down to 17%
Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6		Dims down to 14%
Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6		Dimsdown to 13%
GE		Z WAVE	ZW3005	Best	1	6		Dims down to 3%
Universal	Legrand	Adorne SoftTap	ADTP703TU	Good	1	6		Dims down to 23%, minor humming
		Miro Decorator	DRD4-W	Best	1	6		Dims down to 3%
		Harmony	H703PTUTC	Good	1	6		Dims down to 26%, minor humming
		Adorne Whisper	ADWR700MMTUNW2	Good	1	6		Dims down to 1%, minor humming
		Adorne Touch	ADTH700MMTUNW2	Good	1	6		Dims down to 1%, minor humming
	Cooper	Decorator	DA106P-CZ-K-L	Best	1	6		Dims down to 1%
		Skye	SAL06P-W-K-L	Best	1	6		Dims down to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

Contact Information:
Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2017 Bulbrite Industries Inc.
All Rights Reserved.