

**DESCRIPTION**

Provide power to multiple holiday light strings and lit decorations with this outdoor power outlet yard stake.

**FEATURES**

- Can be turned on or off using RF remote (included) or with the switch on the stake
- Remote must be within 100 ft. of yard stake in order to operate the stake
- Has 6 outlets, each protected with water-proof covers
- Comes with 6 ft. SJTW 14AWG/3C 3-prong power cord
- Lighted on/off switch with built-in circuit breaker
- Installs with included 12-inch plastic yard stake

**LISTINGS**

- UL rated for indoor and outdoor use
- FCC Part 15

**ELECTRICAL**

- Voltage: 125V
- Amperage: 15A

**WARRANTY**

- 1 year prorated warranty; see [pltsolutions.com](http://pltsolutions.com) for warranty details

**APPLICATIONS**

- Holiday Lighting

project name	type
catalog number	
comments	voltage
approved by	date



<b>PERFORMANCE</b>	Maximum Wattage	1875W
	Maximum Amperage	15A
<b>ELECTRICAL</b>	Input Voltage	125V
	Wire Gauge	14 AWG
<b>OUTLETS</b>	NEMA	5-15R
	# of Outlets	6
<b>REMOTE</b>	Battery	3V (CR2032)
<b>CONSTRUCTION</b>	Housing	Plastic
	Finish	Garden Green
<b>LISTINGS</b>	Certifications	UL Listed, FCC
	Environment	Indoor/Outdoor Rated

# PERFORMANCE SUMMARY

Item #	Max. Wattage	Max. Amperage	Voltage	# of Outlets	Remote Capable	Finish
PLTS-12331	1875W	15A	125V	6	Yes	Garden Green

## DIMENSIONS



### **BODY**

Length: 8.3"

Width: 3.8"

Depth: 2.3"

### **YARD STAKE**

Length: 12.5"

Width: 1.5"

### **REMOTE CONTROL**

Length: 2.8"

Width: 1.5"

Depth: 0.6"

## WARNINGS

- For temporary use. Do not exceed 90 days.
- If amperage of lighting is unknown, do not connect more than 140 screw-base lamps (C7 or C9) or 12 mini light strings to this power stake.
- Connector must be at least 6 inches above the ground.
- Do not use outdoors if temperatures drop below -40°F (-40°C)