

90+ LIGHTING



MODEL	A19 3.8W 350LM 2700K E26
SKU	SE-350.115

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	VIVE	MRF2S-6CL-WH	NC	
	CASETA	PD-6WCL-WH	NC	
	DIVA		DV-600P-WH	NC
			DVELV-300P-WH	OK
	DIVA C*L	DVWCL-153PH-WH	OK	
	MAESTRO		MACL-153M-WH	OK
			MAELV-600-WH	OK
	SKYLARK		S-603P-WH	NC
			SELV-300P-WH	OK
			SCL-153P-WH	NC
			SLV-600-WH	NC
			SPSELV-600M	OK
	NOVA T		NTELV-300-WH	NC
			NTLV-600-277-WH	OK
	RADIO RA2		RRD-6CL-WH	OK
-		CT-600PR-WH	OK	
ARIADNI		AYCL-153P-WH	NC	
LEVITON	DECORA	R62-6674-POW	NC	
	-	C22-6672-1LW	OK	
	-	R70-6631-1LW	OK	

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.