## 90+LIGHTING



MODEL	MR16 6W 500LM 2700K GU10 15D
SKU	SE-350.185

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
	MAESTRO	MRF2S-6CL-WH	OK	
	Caseta	PD-6WCL-WH	OK	
	DIVA	DV-600P-WH	OK	
		DVELV-300P-WH	OK	
	DIVA C*L	DVWCL-153PH-WH	OK	
	MAESTRO	MACL-153M-WH	OK	
		MAELV-600-WH	OK	
	Skylark	S-603P-WH	OK	
		SCL-153P-WH	NC	
		SELV-300P-WH	OK	
		SLV-600-WH	OK	
	Spacer	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
		NTLV-600-277-WH	OK	
	Radio RA2	RRD-6CL-WH	OK	
	Ariadni	AYCL-153P-WH	NC	
	-	DIVA DVCL-153P	OK	
LUTRON	-	MAELV-600	OK	
LUTRON	-	SYLNRK SELV-300P	OK	
	-	SYLNRK CTELV-303P	OK	
	-	DIVA DVELV-300P	OK	
	-	DIVA DVELV-303P-AL	OK	
	-	Radio RA2 RRD-6NA	OK	
	-	DIVA DVELC-303P-WH	OK	
	-	Lumea LGCL-153P	OK	
	-	SYLNRK S-600P	OK	
- - - - - - - - - - -	-	SYLNRK CTCL-153P	OK	
	-	Lumea LGCL-153PL	OK	
	-	1B3211	OK	
	-	1C13l1	OK	
	-	VTELV-600M	OK	
	-	SLV-600P	OK	
	-	DV-603P-WH	OK	
	-	DVWCL-153PH/jsb1-85	OK	
	-	NTLV-600-WH/jsb1-88	OK	
	-	MRF2-3LDH	OK	
	Decora	R62-6674-P0W	OK	
	-	6674	OK	
	_	6633-P	OK	
LEV (ITON)	-	52136	OK	
LEVITON	-	6161	OK	
	-	RPI06-1/jsb1-103	OK	
F	-	1PL06/jsb-92	OK	
	-	RTD01-10Z/jsb-100	OK	
+	_	Maxxima DMB01/6	OK OK	
MAXXIMA	-	Maxxima DMA02	OK	
FEIT	_	LGCL-153PLH-WH	OK OK	
	-	LUTRO-S-600P-WH	OK OK	
	-	LEVITON-C20-06681-12A	OK OK	
	<u> </u>	2EVITOIN 020 00001 12A	- Oit	

## DIMMER COMPATIBILITY

OK	Dims to < 15%	
OK	Dims to 15 - 30%	
NC	Not Compatible	

## 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
  2) The results may be different for each application depending on the installation conditions.
  3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.

- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.

For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

