



COLOR SELECTABLE RETROFIT LED DOWNLIGHT

WARNING, CAUTION, SAFETY AND INSTALLATION INSTRUCTIONS

WARNING

- Installation, service, and maintenance of luminaires should be performed by a qualified licensed electrician.
- Before starting installation, please read instructions and keep for future reference.
- To avoid electrical shock, do not turn on fixture with missing or damaged lens.
- There are no serviceable parts inside of the LED module.

CAUTION

- Supply conductors (power wiring) connecting the fixture must be rated for a minimum of 90°C (194°F).
- Do not make or alter any holes in the wiring enclosure, or in any of the electrical components.
- Do not alter, relocate, or remove wiring, lamp holders, power supply, or any other electrical component.
- These retrofit luminaires are designed to install in standard 5"-6" recessed downlight housings only. Do not attempt to alter for other size or purpose. Before beginning installation, confirm housing compatibility by checking the interior of the housing for a manufacturer's part number and specifications, or measure the diameter of the housing.
- The recessed housing must have a minimum measured inside diameter of 5-1/4" and a maximum inside diameter of 6-3/4".

NOTICE

- This downlight is rated Type IC.
- For indoor use only, suitable for damp locations. Prevent the fixture from coming in contact with water or any other liquids to prevent electrical shock.
- Protect the fixture from dust and dirt when painting or during installation.
- Clean with a soft damp cloth only. Do not use any chemical cleaners.
- This luminaire can be dimmed with a standard Triac dimmer.

Installation Instructions

Installation for 5-6 Inch (See FIG. 1-4)

<ol style="list-style-type: none">1. Turn off the power supply, and select the position of your CCT switch.2. If installing into 6" housings, no adjustment of the V springs is needed. Go to step 3. If installing into 5" housing, adjust the V spring so that it fits 5" housing (FIG. 1)3. Thread the socket adapter into the socket (FIG. 2).4. Plug the female connector of the retrofit trim onto the male connector of the socket adapter assembly (FIG. 3)5. Squeeze both V spring arms together and insert into the V spring slots of the housing. Tuck all wires into the housing and carefully push the retrofit downlight into the housing (FIG.4).	<p>FIG.1: A close-up diagram showing a hand adjusting a V Spring on a CCT Switch. The switch is labeled 'OFF' and has a 'V Spring' label pointing to the adjustment mechanism.</p> <p>FIG.2: A diagram showing a socket adapter being inserted into an 'Existing housing' which is mounted on a 'Ceiling'.</p> <p>FIG.3: A diagram showing the retrofit trim being connected to the socket adapter assembly.</p> <p>FIG.4: A diagram showing the retrofit downlight being inserted into the housing, with wires being tucked into the housing.</p>
--	--



Dimming

This product is suitable for dimming. For 5-100% light control, use with most standard dimmers, including Lutron SCL-153P, DVCL-153P, TG-600PH-LA, MACL-153MR-WH, MACL-153ME, and DV-600P, or Leviton CL-6674, CL-6672, CL-6683, IPL06, and 153M-ES.

⚠ WARNING

- Before installing, servicing, or performing routine maintenance upon this equipment, follow these general precautions.
- To reduce the risk of death, personal injury, or property damage from fire, electric shock, falling parts, cuts/abrasions, and other hazards, read all warnings and instructions included with and on the fixture box and all fixture labels.
- Proper grounding of the original housing is required to ensure safety.
- Power must be turned off at the breaker before installation or maintenance.
- This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
- Wear gloves and eye protection at all times while installing, servicing, or performing maintenance on the luminaire, and avoid direct eye exposure to the light source while it is on.
- To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.
- Do not install damaged product. Inspect luminaire for damage that may have occurred during transit. If damaged, contact the manufacturer immediately.
- These instructions do not purport to cover all details or variations in equipment nor to provide every possible contingency to meet in connection with installation, operation, or maintenance. Should further information be desired or should particular problems arise which are not covered sufficiently for the purchaser's or owner's purposes, contact the manufacturer.

⚠ ADVERTENCIA

- Antes de instalar, reparar o realizar el mantenimiento de rutina de este equipo, siga estas precauciones generales.
- Para reducir el riesgo de muerte, lesiones personales o daños a la propiedad por fuego, descarga eléctrica, caída de piezas, cortes / abrasiones y otros peligros, lea todas las advertencias y instrucciones incluidas con y en la caja del dispositivo y todas las etiquetas del dispositivo.
- Se requiere una conexión a tierra adecuada de la carcasa original para garantizar la seguridad.
- Se debe apagar la energía en el disyuntor antes de la instalación o el mantenimiento.
- Este producto debe ser instalado de acuerdo con el código de instalación aplicable por una persona familiarizada con la construcción y operación del producto y los peligros involucrados.
- Utilice guantes y protección para los ojos en todo momento durante la instalación, el servicio o el mantenimiento de la luminaria, y evite la exposición directa de los ojos a la fuente de luz mientras está encendida.
- Para evitar daños o abrasiones en el cableado, no exponga el cableado a bordes de láminas de metal u otros objetos afilados.
- No instale un producto dañado. Inspeccione la luminaria en busca de daños que puedan haber ocurrido durante el tránsito. Si está dañado, comuníquese con el fabricante de inmediato.



COLOR SELECTABLE RETROFIT LED DOWNLIGHT

WARNING, CAUTION, SAFETY AND INSTALLATION INSTRUCTIONS

- Estas instrucciones no pretenden cubrir todos los detalles o variaciones en el equipo ni proporcionar todas las posibles contingencias a cumplir en relación con la instalación, operación o mantenimiento. Si desea obtener más información o si surgen problemas particulares que no están suficientemente cubiertos para los propósitos del comprador o propietario, comuníquese con el fabricante.