

# Color and Wattage Selectable LED Panel Fixture w/ Emergency Backup

### **DESCRIPTION**

Create a modern look in your space by installing these color and wattage selectable LED panels. These fixtures come with a built-in emergency backup, ensuring you have light in the event of a power failure.

# **FEATURES**

- Efficiently replaces up to a 3 lamp fluorescent fixture
- Built-in emergency backup operates fixtures for at least 90 minutes in the event of a power failure; recharges in 24 hours
- · Red test switch located on the frame
- 0-10V dimming
- Light output varies depending on wattage and color temperature selected; see Selectable Table for full breakdown
- Wattage and color temperature is selectable via switches on the driver box; see installation instruction for more information

### **LISTINGS**

- UL rated for damp locations
- IC Rated
- FCC
- DesignLights Consortium® 5.1 Standard meets the requirements for the highest DLC qualification for efficacy and lumen maintenance

### **PERFORMANCE**

• CRI: 80

CCT: 3500K, 4000K, and 5000K

LED L70 Life Hours @ 70°C: >100,000 hours

# **EMERGENCY OPERATION**

Operation: 90 minutes Charging Time: 24 Hours Input Voltage: 100-277V

Output Power: 8W

Output Lumens: 1000 to 1500

## **THERMAL**

• -4°F to 122°F (-20°C to 50°C) operating temperature

# **ELECTRICAL**

• THD: <20%

• Power Factor: >0.9

Input Voltage: 120-277V


Dimmable power supply (0-10V)

· Surge Protection: 2kV

# **INSTALLATION**

 Designed for recessed installation in a T-grid ceiling; see installation instructions for more information

Project name	Туре
Catalog number	
Comments	Voltage
Approved by	Date









### CONSTRUCTION

- Stamped sheet metal housing with white powder coat finish
- Frosted PS lens protects LEDs while evenly distributing light

## WARRANTY

 5-year limited warranty; see pltsolutions.com for warranty details

### **APPLICATIONS**

- Conference Rooms
- Retail
- Offices
- Hospitality
- Healthcare
- Schools
- Reception Areas
- Corridors
- Foyer

# **PERFORMANCE SUMMARY**

Item #	Size	Watts*	сст*	CRI	Dimming	Voltage	Emergency Operation	Recharge Time	Emergency Output Lumens	Replaces	Default Settings	DLC #	DLC Level
PLT-90350	2x2	25/30/40	3500K/4000K5000K	80	0-10V	120-277V	90 minutes	24 Hours	1000 to 1500	2 or 3 Lamp Fluorescent	40W, 5000K	PLTM521511	5.1 Standard
PLT-90351	2x4	30/40/50	3500K/4000K5000K	80	0-10V	120-277V	90 minutes	24 Hours	1000 to 1500	3 Lamp Fluorescent	50W, 5000K	PLTM532511	5.1 Standard

<sup>\*</sup> See Selectable Table for full breakdown

# **SELECTABLE TABLE**

Item #	Wattage	ССТ	Lumens	Efficacy	
		3500K 3208		128	
	25	4000K	3386	135	
		5000K 3253		130	
		3500K	3862	128	
PLT-90350	30	4000K 4124		137	
		5000K	3818	130	
		3500K	4832	120	
	40	4000K 5222		130	
		5000K	4882	122	
		3500K	3800	127	
	30	4000K	3990	133	
		5000K	3880	129	
		3500K	5000	125	
PLT-90351	40	4000K	5300	133	
		5000K	5100	128	
		3500K	5975	120	
	50	4000K	6200	124	
		5000K	6100	122	

# **FIXTURE DIMENSIONS**

# **2X2 DIMENSIONS**

Length: 23.7"

Height: 1.5"

Width: 23.7"

Weight: 6.88 lbs

# 23.7" 23.7" 1.5"


# **2X4 DIMENSIONS**

Length: 47.8"


Height: 1.5"

Width: 23.7"

Weight: 10.32 lbs



# **2X2 DIMENSIONS**



# **2X4 DIMENSIONS**

