



7W LED A15 3000K FILAMENT BASICS DIMMABLE

Item #776640

Ordering Code LED7A15/30K/FIL/D/B UPC 739698819556

- Incandescent A15 replacement
- Rated for use in totally enclosed fixtures
- For damp location use
- Low-cost alternatives to our most popular filament styles
- Compatible with most dimmers, see Bulbrite.com for compatibility charts









## **TECHNICAL SPECIFICATIONS**

Item # 776640	Watts 7	Bulb Type A15	Base E26	Volts 120	Finish/Description Clear	Beam Angle (°) 320°	Color Temperature (CCT) 3000K
Color Soft White Light	CRI 80	Lumens 800	CBCP N/A	Average Hours 10000	M.O.L. (inches) 3.26	M.O.D. (inches) 1.89	Incandescent Equivalent 60
Energy Star N	DLC N	Title 24 Compliant	Safety Rated UL	Safety Rating Typ	eEnclosed Rated Y	Dimmable Y	Warranty 2

Order Multiple QTY 10

## **APPLICATION SUGGESTIONS**







Ceiling Fixture

Chandelier



## **Dimmer Compatibility Guide**

Product Family Name:

tem Number: Ordering Code: Item Number: 776639 LED7A15/27K/FIL/D/B 776640 LED7A15/30K/FIL/D/B 776641 776642 LED7A15/27K/FIL/M/D/B LED7A15/30K/FIL/M/D/B

oracing code.					Lamps pe	er Dimmer	
	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
		IllumaTech	IPI06	Best	1	6	Dims down to 1%
	Leviton	SureSlide	6633-P	Best	1	6	Dims down to 1%
<u> </u>		Vizia	VPI06-1LZ	Best	1	6	Dims down to 1%
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 1%
Incandescent/Halogen (Triac/Phase		Lumea	LGCL-600	Best	1	6	Dims down to 1%
Cut/Leading Edge Dimmers)		Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
<u>_</u>		Maestro	MAW-600	Good	3	6	Dims down to 1%
	Legrand	Titan	CD703-PW	Good	3	6	Dims down to 1%
		Harmony	D703-PTC	Good	3	6	Dims down to 1%
		Harmony	H703-PTC	Good	3	6	Dims down to 1%
	Leviton	IllumaTech	IPL06	Best	1		Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%
		Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Sunnata	STCL - 153	Best	1	6	Dims down to 1%
CFL/LED		Diva	DVCL-153PL	Best	1		Dims down to 1%
0.17220	Lutron	Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
	Legrand	Radiant	RHCL453PW	Best	1	6	Dims down to 1%
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%
	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
		IllumaTech	IPE04	Good	1	6	Dims down to 1%, not smooth dimming
<u>_</u>		Decora	6615-P	Good	1	6	Dims down to 1%, not smooth dimming
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%
Electronic Low Voltage		Diva	DVELV-300P	Best	1	6	Dims down to 1%
		Maestro	MAELV-600	Best	1	6	Dims down to 1%
		Skylark	SELVB-300P	Best	1	6	Dims down to 1%
<u>_</u>		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
	Legrand	Scene Director	SCELV	Best	1	6	Dims down to 1%
	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 1%, flickering at LE with 2
		Decora	6613-P	Best	1	6	Dims down to 1%
Magnetic Low Voltage	Lutron	Maestro	MALV-600	Not compatible	1	6	Not turn on with 1-6
		Harmony	DLV703-PW	Good	2	6	Dims down to 1%
	Legrand	Titan	CDLV703-PW	Good	2	6	Dims down to 1%
			•				
	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1		Dims down to 1%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 1%
Smart Dimmer	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1		Dims down to 1%
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%
	Legrand	Adorne SofTap	ADTP703TU	Good	2	6	Dims down to 5%
		Miro Decorator	DRD4-W	Bad	1	6	Flickering at HE with 1-6
		Harmony	H703PTUTC	Bad	3	6	flickering at LE with 3-6
Universal		Adorne Whisper	ADWR700MMTUW2	Best	1		Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1		Dims down to 1%
		n	DAL06P-C2-K-L	Good	2	6	Dims down to 1%
	Cooper	Decorator Skye	SAL06P-W-K-L	Good	2	6	Dims down to 1%  Dims down to 1%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating				
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.			
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.			
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.			
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.			
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.			
Low End (L.E.) Dead Travel	becommend now more, it any, used dover exists at the doping bottom of the difference of the state of which the shade and the sha			