



VALUE SELECT MR FAMILY

MODEL

Model: 6.5MR16DIM/xxxxyyy/35W
 6.5MR16DIM/xxxxyyy
 6GU10DIM/xxxxyyy

Where xxx means 824-965 which indicates CRI and color temperature
 Where yyy means beam angle



ELECTRONIC DIMMER SWITCH COMPATIBILITY

Model: 6.5MR16DIM/xxxxyyy/35W

Brand	Series	Model	Load (w)	Hatch												Lightech		
				RS12-15M-LED		RS12-30M-LED		RS12-60M-LED		RS12-80M (DC1931)				RS12-60M		LET60	LET75	
				1	23456	1	23456	1	23456	1	2	3	4	5	6	1	23456	1
Lutron	Maestro	MAELV-600	600	0-100%	0-100%	0-100%	10-100%	0-100%	20-100%	x				20-100%	20-100%	10-100%	10-100%	x
	Skylark Contour	CTELV-303P	300	0-100%	0-100%	0-100%	10-100%	0-100%	10-100%	x	20-100%	x	20-100%	20-100%	10-100%	10-100%	x	
	Diva	DVELV-300P	300	0-100%	0-100%	0-100%	10-100%	0-100%	20-100%	x				20-100%	10-100%	10-100%	x	
	Nova	NTELV-600	600	10-100%		10-100%		10-100%		x				10-100%		10-100%	x	
	Caseta	PD-5NE	250	0-100%	10-100%	0-100%	10-100%	0-100%		x				20-100%	10-100%	10-100%	x	
Leviton	Illumatech	IPE04-1LZ	300	x		x		x		x				x		x	x	
Cooper	Aspire	9536	1,000	x		x		x		x				x		x	x	

ELECTRONIC DIMMER SWITCH COMPATIBILITY

Model: 6.5MR16DIM/xxxxyyy

Brand	Series	Model	Load (w)	Hatch												Lightech		
				RS12-15M-LED		RS12-30M-LED		RS12-60M-LED		RS12-80M (DC1931)				RS12-60M		LET60	LET75	
				1	23456	1	23456	1	23456	1	2	3	4	5	6	1	23456	1
Lutron	Maestro	MAELV-600	600	0-100%	10-100%	0-100%	10-100%	0-100%		x	20-100%				20-100%	0-100%	10-100%	x
	Skylark Contour	CTELV-303P	300	0-100%		0-100%	10-100%	0-100%	10-100%	x	20-100%				20-100%	0-100%	10-100%	x
	Diva	DVELV-300P	300	0-100%		0-100%	10-100%	0-100%	20-100%	x	20-100%				20-100%	10-100%	10-100%	x
	Nova	NTELV-600	600	10-100%		10-100%		10-100%		x	20-100%				10-100%		10-100%	x
	Caseta	PD-5NE	250	0-100%	20-100%	0-100%	10-100%	0-100%	10-100%	x	20-100%				20-100%	10-100%	10-100%	x
Leviton	Illumatech	IPE04-1LZ	300	x		x		x		x				x		x	x	
Cooper	Aspire	9536	1,000	x		x		x		x				x		x	x	

x: Not compatible



VALUE SELECT MR FAMILY

MAGNETIC DIMMER SWITCH COMPATIBILITY

Model: 6.5MR16DIM/xxxxyyy/35W

Brand	Series	Model	Load (w)	Cooper		Elco	Hatch	Juno	Halo
				TF-149911-TP120	TF-149911-TP	SSH-6626002	DL1250B-H	VF180-210	QE001292AS
Lutron	Abella	ABLV-1000M	1,000	10-100%	10-100%	10-100%	10-100%	20-100%	10-100%
	Skylark	SLV-600P	600	10-100%	10-100%	10-100%	10-100%	10-90%	10-100%
	Maestro	MALV-600	600	10-100%	10-100%	20-100%	20-90%	20-90%	20-90%
Legrand	Adorne	ADTP703TU	700	20-90%	20-100%	20-100%	20-90%	20-90%	10-80%
	Harmony	H703PTU	600	Not Compatible					
Leviton	Sure Slide	6613-P	600	0-100%	0-100%	0-100%	0-90%	0-90%	0-100%
	VIZA+	VPM10	1,000	10-100%	10-100%	10-90%	0-100%	20-100%	0-100%
Cooper	Devine	DAL06P	300	0-100%	0-100%	Not Compatible	0-100%	10-100%	10-100%
	Aspire	9536	600	Not Compatible					

MAGNETIC DIMMER SWITCH COMPATIBILITY

Model: 6.5MR16DIM/xxxxyyy

Brand	Series	Model	Load (w)	Cooper		Elco	Hatch	Juno	Halo
				TF-149911-TP120	TF-149911-TP	SSH-6626002	DL1250B-H	VF180-210	QE001292AS
Lutron	Abella	ABLV-1000M	1,000	10-100%	10-100%	10-100%	10-100%	20-100%	10-100%
	Skylark	SLV-600P	600	10-100%	10-100%	10-100%	10-100%	10-90%	10-100%
	Maestro	MALV-600	600	10-100%	10-100%	20-100%	20-90%	20-90%	20-90%
Legrand	Adorne	ADTP703TU	700	10-100%	10-100%	20-100%	20-100%	20-90%	10-90%
	Harmony	H703PTU	600	Not Compatible					
Leviton	Sure Slide	6613-P	600	0-100%	0-100%	0-100%	0-90%	0-90%	0-100%
	VIZA+	VPM10	1,000	0-100%	0-100%	10-90%	0-100%	20-100%	0-100%
Cooper	Devine	DAL06P	300	0-100%	0-100%	Not Compatible	0-100%	10-100%	10-100%
	Aspire	9536	600	Not Compatible					

DIMMER COMPATIBILITY

Model: 6GU10DIM/xxxxyyy

Brand	Series	Model	Load (w)	Dimming Range	Dimmability
Lutron	Diva	DV-600P	600	10-100%	Compatible
	Toggler	TG-600P	600	10-100%	Compatible
	Skylark Contour	CTCL-153P	150	10-100%	Compatible
	Diva	DVCL-153P	150	10-100%	Compatible
	Maestro	MACL-153M	150	10-100%	Compatible
Leviton	Sureslide Decora	6674	600	10-100%	Compatible
	Trimatron	6602	600	10-100%	Compatible

GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps. Dimmer and/or transformer maximum load in the dimmer compatibility table should not be exceeded.