

145 West Commercial Ave. Moonachie, NJ 07074

Dimmer Compatibility Guide

Product Family Name: Item Number: Ordering Code: Item Number: Ordering Code: LED5T9/21K/11/FIL-NOS/3 LED5T9/27K/11/FIL/3 LED5T9/30K/11/FIL/3

Ordering Code:					Lamps per	Dimmer	
					Recommended	Maximum	
	Manufacturer	Product	Model Number	Overall Rating	Minimum	Tested*	Notes
	Leviton	IllumaTech	IPI06	Good	1	6	Minor flickering at LE with 4-6
		SureSlide	6633-P	Good	1	6	Minor flickering at LE with 4-6
		Vizia	VPI06-1LZ	Good	1	6	Minor flickering at LE with 2
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 1%
ncandescent/Halogen (Triac/Phase		Lumea	LGCL-600	Best	1	6	Dims down to 1%
Cut/Leading Edge Dimmers)		Diva	DV-600	Best	1	6	Dims down to 1%
cuty ceauning Euge Diminiersy		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Bad	5	6	Dims down to 1%
	Legrand	Titan	CD703-PW	Good	4	6	Dims down to 1%
		Harmony	D703-PTC	Good	4	6	Dims down to 1%
		Harmony	H703-PTC	Good	4	6	Dims down to 1%
	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 1%
		Decora	6672	Best	1	6	Dims down to 1%
		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
CFL/LED		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
		Radiant	RHCL453PW	Best	1	6	Dims down to 1%
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%
•						*	
	Leviton	Vizia	VPE04	Good	1	6	Minor flickering at LE with 1-6
		IllumaTech	IPE04	Good	1	6	Minor flickering at LE with 1-6
		Decora	6615-P	Best	1	6	Dims down to 15% with 1-6
	Lutron	Skylark Countour	CTELV-303P	Good	1	6	Minor flickering at LE with 1-6
Electronic Low Voltage		Diva	DVELV-300P	Good	1	6	Minor flickering at LE with 1-6
		Maestro	MAELV-600	Good	1	6	Minor flickering at LE with 1-6
		Skylark	SELVB-300P	Good	1	6	Minor flickering at LE with 1-6
		VIERTI	VTEL-600M-W	Good	1	6	Minor flickering at LE with 1-6
_	Legrand	Scene Director	SCELV SCELV	No compatible	1	6	Fl;ickering from HE to LE with 1-
	Legiana	Scene Director	JCELV	140 compatible	-		Trickering from the to be with 1
	Leviton	Vizia	VPM-06	Good	1	6	Flickering at LE with 2
		Decora	6613-P	Good	1	6	Flickering at Med with 1
Magentic Low Voltage	Lutron	Maestro	MALV-600	Not compatible	1	6	Flickering at Wed With 1
magenia zon voltage	LULIOII	Harmony	DLV703-PW	Good	1	6	Dims down to 1%
	Lannand	Titan	CDLV703-PW	Good	1	6	Flickering at Med with 2
	Legrand	IIIdii	CDLV/U3-PW	G000	1	ь	riickering at ivied with 2
	Louiton	Docora Digital (Pluotooth)	DDMX1-BLZ	Best	2	6	Dims down to 1%
	Leviton	Decora Digital (Bluetooth)					
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%
Court Birming	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1		Dims down to 1%
Smart Dimmer	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Minor flickering at LE with 5
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	2	6	Dims down to 1%
	GE	Z WAVE	ZW3005	Best	2	6	Dims down to 1%
_	Legrand	1					Tay 1
		Adorne SofTap	ADTP703TU	Good	3	6	Dims down to 10%
		Miro Decorator	DRD4-W	Bad	1	6	Flickering from HE to LE with 1-6
		Harmony	H703PTUTC	Not compatible	1	6	
Universal		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Flickering at LE with 1
	cooper	Skye	SAL06P-W-K-L	Good	1	6	Flickering at LE with 1

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating				
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.			
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.			
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.			
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.			
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.			
Low End (L.E.) Dead Travel	Determines now moun, it any, usay date costs at the top and outcomes are dismined a range. Dead dated is when the silver tall be moved without affecting the light level.			

Commax information:
Bulbrite Industries Inc.
185 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
Email: ProductSupport@bulbrite.com
02024 Bulbrite industries Inc.
All Rights Reserved.