

LED WALL LIGHT

Model No. LIS-WL1000-12

This smart RGBW outdoor wall light supply takes full control of your outdoor lighting with the user-friendly mobile app. Easily change colors, adjust brightness, set schedules, and create custom lighting scenes right from your smartphone. Compatible with 4" US standard J-BOX to easy install. Die-casting aluminum body with powder coating,Anti-UV PC diffuser improves lighting performance. Connect APP with 2.4G wifi or bluetooth, Works with Amazon Alexa, and Google Assistant. Weather resistant and rust resistant, well-constructed and high quality. Suitable for outdoor and indoor use.





Frosted Plastic Lens

150W REPLACEMENT 18W RGBW



Electrical Specifications


Model No.	Input Power	Input Voltage	Lumen Output	Beam Angle	Center Beam	ССТ
LIS-WL1000-12	18 W	120 V	1260 lm	180°	N/A	RGBW

CRI	Luminous Efficacy	Power Factor	Input Current	Base	Lamp Lifespan	Estimated Yearly Cost
80	70 lm/W	0.95	0.16 A	Direct Wiring	40,000 Hrs.	\$2.16

Mechanical Specifications

Rating	Operational Temperature	Inner Box QTY.	Master Box QTY.	Dimensions(in.)	UPC Code
Wet Rated	-4°F - 104°F	1 pcs	10 pcs	4.97"(W) x 3.35"(D) x 12.22" (H)	811174038962

Product Dimensions





Product Photometric Data

Euri Lighting İ A Division of IRTRONIX Inc.

20900 Normandie Avenue Suite B Torrance, CA 90502 | Tel: 888.743.5766 | Fax: 310.787.1166 | www.eurilighting.com ©2022 Euri Lighting. All Rights Reserved